

REMARKS

Applicant has carefully reviewed the Application in light of the Final Office Action mailed January 16, 2004. At the time of the Final Office Action, Claims 1-10, 14-17, and 21-24 were pending in the Application. Applicant cancels these claims without prejudice or disclaimer. The cancellation of these claims is not the result of any prior art reference, nor has it been done to address any potential deficiency in Applicant's specification. The cancellation of these claims has been done only in an effort to expedite the prosecution of this case. Applicant also adds claims 36-46. The addition of these claims does not add any new matter to the Application. In addition, Applicant has made a series of minor corrections to the specification because of various inaccuracies, which were identified by the Examiner. No new matter has been added to the Application. For the convenience of the Examiner, Applicant has appended a marked-up copy and a clean copy of the specification (reflecting these changes) to this Response. Applicant respectfully requests reconsideration of the pending claims and favorable action in this case.

Priority

The Examiner notes that Applicant has submitted an uncertified copy of the 99112552.7 Application filed in Europe on July 1, 1999 and requests that a certified copy be submitted as is required by 35 U.S.C. 119(b). Because any reference to this application has been removed, Applicant has fully addressed this matter and overcome the objection. The Examiner also notes that Applicant has submitted an uncertified copy of the 01-11594.8 Application filed in Europe on May 31, 2000 and requests that a certified copy also be submitted as is required by 35 U.S.C. 119(b). Applicant has complied with the Examiner's request and provided the certified document, which is appended to this Response.

Claim Objections

The Examiner made numerous objections to the Claims: specifically identifying a number of typographical errors. Applicant again apologizes for these drafting imperfections. Applicant has cancelled the previously pending claims and proffered the new claim set.

Section 102 Rejections

The Examiner provisionally rejects Claims 1-6, 9-10, 14-15, and 21-24 under 35 U.S.C. §102(e) as being anticipated by copending Application 09/608,657, which has a common inventor and a common assignee with the instant application. This rejection is now moot in light of the cancellation of those claims and the addition of claims 36-46. The addition of these Claims is a result of multiple conversations between Applicant and Examiner Kim, who is handling this matter. The resultant claim strategy was developed with exceptional cooperation from the participating parties. Accordingly, Applicant is confident in the patentability of the pending claims.

In addition, in the context of the §102 rejection Applicant would like to respectfully remind the Examiner that a claim is anticipated only if each and every element as set forth in the claim is found, either expressly or inherently described, in a single prior art reference.¹ In addition, “[t]he identical invention must be shown in as complete detail as is contained in the . . . claims” and “[t]he elements must be arranged as required by the claim.”² In regard to inherency of a reference, “[t]he fact that a certain result or characteristic may occur or be present in the prior art is not sufficient to establish the inherency of that result or characteristic.”³ Thus, in relying upon the theory of inherency, an Examiner must provide a basis in fact and/or technical reasoning to support the determination that the allegedly inherent characteristic necessarily flows from the teachings of the applied prior art.⁴

It is respectfully submitted that none of the references anticipate Independent Claim 1. Accordingly, Independent Claim 1, along with its corresponding dependent claims, are allowable over the previously-cited references. Notice to this effect is respectfully requested in the form of a full allowance of these claims.

Section 103 Rejections

The Examiner rejects claims 1, 3-4, 9-10, 14-15, and 22 under 35 U.S.C. §103(a) as being unpatentable over U.S. Patent No. 5,647,035 issued to Cadeddu et al. (hereinafter

¹ *Verdegaal Bros. v. Union Oil Co. of California*, 2 USPQ 2d 1051, 1053 (Fed. Cir. 1987); M.P.E.P. §2131.

² *Richardson v. Suzuki Motor Co.*, 9 USPQ 2d 1913, 1920 (Fed. Cir. 1989); *In re Bond*, 15 USPQ 2d 1566 (Fed. Cir. 1990); M.P.E.P. §2131 (*emphasis added*).

³ M.P.E.P. §2112 (citing *In re Rijckaert*, 9 F.3d 1531, 1534, 28 USPQ 2d 1955, 1957 (Fed. Cir. 1993) (*emphasis in original*)).

⁴ M.P.E.P. §2112 (citing *Ex Parte Levy*, 17 USPQ 2d 1461, 1464 (Bd. Pat. at App. and Inter. 1990) (*emphasis in original*)).

“*Cadeddu*”) in view of Gerstel et al. (article entitled “Optical layer survivability: a services perspective”) (hereinafter “*Gerstel*”). The Examiner rejects claims 1-5, 7-10, 14-17, and 21-22 under 35 U.S.C. §103(a) as being unpatentable over European Patent Application EP 920153 A2 (hereinafter “*Shiragaki*”) in view of *Cadeddu*. The Examiner rejects claims 6 and 24 under 35 U.S.C. §103(a) as being unpatentable over *Shiragaki et al.* in view of *Cadeddu* as applied to Claims 5 and 14 and, further, in view of *Karasan et al.* (article entitled “Optical restoration at the wavelength-multiplex-section level in WDM mesh networks”). The Examiner also rejects claims 11-13 under 35 U.S.C. §103(a) as being unpatentable over U.S. Patent No. 6,259,837 issued to de Boer et al. (hereinafter “*de Boer*”) in view of *Cadeddu* (as applied to Claim 3 above under 35 U.S.C. §102(b)). The Examiner also rejects Claims 11-13 under 35 U.S.C. §103(a) as being unpatentable over *de Boer* in view of *Shiragaki, et al.* and in view of *Cadeddu* (as applied to Claim 3 above under 35 U.S.C. §103(a)). The Examiner also rejects Claims 25-35 under 35 U.S.C. §103(a) as being unpatentable over *Shiragaki, et al.* in view of *Karasan, et al.* With respect to this §103 rejection, Applicant has cancelled those rejected claims. Thus, the §103 rejection is now moot in light of the cancellation of those claims.

Double Patenting and Provisional Rejections

The Examiner provisionally rejects claims 1-6, 9, 14-15, and 21-22 under the judicially created doctrine of obviousness-type double patenting as being unpatentable over claims 1-12 and 14-21 of copending Application No. 09/608,657 in view of *Gerstel*. This rejection is now moot in light of the cancellation of those claims. Applicant respectfully submits that the newly added claims are patentably distinct from the copending application. Accordingly, Applicant has overcome the double patenting rejection. Notice to this effect is respectfully requested.

CONCLUSION


Applicant has now made an earnest attempt to place this case in condition for immediate allowance. For the foregoing reasons and for other reasons clear and apparent, Applicant respectfully requests reconsideration and allowance of the pending claims.

Applicant believes that no fee is due. If this is not correct the Commissioner is hereby authorized to charge additional fees or credit any overpayments to Deposit Account No. 02-0384 of Baker & Botts, L.L.P.

If there are matters that can be discussed by telephone to advance prosecution of this application, Applicants invite the Examiner to contact its attorney at the number provided below.

Respectfully submitted,

Baker Botts L.L.P.
Attorneys for Applicant


Thomas J. Frame
Reg. No. 47,232

Date February 16th, 2004

CORRESPONDENCE ADDRESS:

2001 Ross Avenue, Suite 600
Dallas, TX 75201-2980
(214) 953-6675
(213) 661-4675

05073

Patent Trademark Office

AUTOPROTECTED OPTICAL COMMUNICATION RING NETWORK

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is related to and claims benefit of priority to (i) European Patent Application No. 991125527.7, filed 01 July 1999, (ii) U.S. Provisional Patent Application Serial No. 60/142,534, filed July 7, 1999, entitled
5 "AUTOPROTECTED OPTICAL COMMUNICATION RING NETWORK,"
and (iii) European Patent Application No. 01-11594.8, filed 31 May 2000, all of
which are incorporated herein by reference.

TECHNICAL FIELD OF THE INVENTION

10 The present invention relates to an autoprotected optical communication ring network, in particular a WDM (Wavelength Division Multiplexing) autoprotected optical communication ring network of the type including a plurality of nodes connected to each other in pairs by means of respective optical connections susceptible to failure, each connection comprising at least a first and a second optical
15 carrier having opposite transmission directions.

BACKGROUND OF THE INVENTION

"Optical communication ring network" here means not only a communication network configured as a whole as a ring but, in general, any section of a network comprising a plurality of nodes and branches and arranged, at least temporarily, in a ring configuration.

Specifically, the present invention tackles the problem of making a ring network with self-healing capabilities, i.e. capabilities of managing failures which may arise in the connections between the network nodes.

"Failure" here means any event which may affect the physical optical carriers (e.g. breakage or interruption of an optical fiber) and/or the devices of the network operating on the transmitted signals (e.g. receivers; demultiplexers, amplifiers, etc.), in such a way as to bring about a situation of degradation of the transmission which is deemed not tolerable; the term "failure" thus should in no way be interpreted as being limited only to events causing the complete interruption of the connection.

The state of the art includes many methods to optically protect a set of wavelength multiplexed optical channels carried by a two-fiber optical ring network.

European Patent Application No. 769859 in the name of the Applicant relates to a transparent optical self-healing-ring communication network in which at least two nodes are optically connected along a first and a second closed optical path having opposite transmission directions. Each node simultaneously feeds its transmitted signals to the first and the second closed optical path, so that the signals travel along complementary arcs of the ring. The receiving node selectively receives the signals from one of the two closed paths and, in case of failure on this closed path, switches reception on the other closed path. The Applicant observes that this Optical Channel Protection method, identifiable as a "Optical Channel 1+1 Dedicated Ring Protection" method, requires that, for each wavelength used on one closed path, the same wavelength cannot be used on the other closed path other than for protection. Thus, with N wavelengths, only N protected channels can be used in the network.

European Patent Application No. 97123013.1-2209 filed on 31/12/97 in the name of the Applicant relates to a method and an apparatus for transparent optical communication with two-fiber bidirectional ring with autoprotection and

management of low priority traffic. The communication network comprises two optical fibers (an external one and an internal one) that interconnect the nodes. According to the proposed technique, if a first and a second node of the network are considered for mutual signal transmission, a high-priority traffic can be set up on a
5 first bidirectional communication path defined between the two nodes on the external and internal fibers, using only an arc of the communication ring defined between the two nodes.

The arc complementary to that just described can be used as a second bidirectional communication path between the two nodes for low-priority traffic,
10 using the same wavelength as the preceding channel. The protection mechanism consists of redirecting the high-priority traffic onto the second path in the case of a breakdown in, or degradation of, communication on the first path, thus losing the low-priority traffic on the second path. This protection method is identifiable as a "Optical Channel 1:1 Dedicated. Ring Protection" method with management of Low-
15 Priority traffic. The Applicant observes that; although this method provides a double capacity with respect to the previous technique, with N wavelengths it is still not possible to protect more than N channels.

The article "A Transparent, All-Optical, Metropolitan Network Experiment in a Field Environment: The "PROMETEO" Self-Healing Ring", F. Arecco et al., IEEE
20 Journal of Lightwave Technology, Vol. 5, Dec 1997, describes a method to provide protection against failures in a metropolitan ring network. According to this method, a working fiber ring is used to carry all the optical channels between nodes, while a protection fiber ring is empty under normal operating conditions. In case of failure, a protection switching takes place at the nodes adjacent to the failure, which
25 reconfigure in such a way to route all the optical channels (i.e. all the wavelengths of the multiplex section) through the protection fiber ring so as to bypass the failure. This protection method is known as "Optical Multiplex Section Protection" method. The Applicant observes that, once more, with N wavelengths it is possible to carry only N protected channels. Moreover, the Applicant further observes that, in this
30 case, it is not possible to have different protection mechanisms (i.e. protection at different layers) for different channels, and that the optical path after a protection reconfiguration can be longer than the ring circumference.

U.S. Patent No. 5,647,035 in the name of CSELT - Centro Studi e Laboratori Telecomunicazioni S.p.A. - provides a ring network communication structure on an optical carrier and a reconfigurable node for said structure. In said structure, a plurality of nodes are interconnected by means of connections comprising at least a first and a second optical carrier, such as an optical fiber. Transmission between two nodes occurs on the ring according to a WDM scheme, by utilizing a first wavelength for communication in one direction on the first carrier and a second wavelength for communication in the opposite direction on the second carrier. The second wavelength on the first carrier and the first wavelength on the second carrier are reserved for protection (protection channels) and are "shared" among all the nodes. Under regular operation conditions of the network, in each node the signals conveyed by the two fibers are detected, processed as required in units of a higher hierarchical level, converted again in optical signals and re-transmitted towards the following node. In the presence of a failure on one of the connections, the nodes adjacent to the failed connection reconfigure themselves to ensure the continuation of communication on the alternative path provided by the ring, by utilizing the first wavelength on the second carrier and the second wavelength on the first carrier. The exemplary embodiment described referring to just two wavelengths λ_1, λ_2 , can be generalized to any number of wavelengths with a corresponding expansion of the described connection; switching matrices of the nxn type may be used.

The Applicant noticed that, in the ring network proposed in US 5,647,035, if multi-wavelength signals have to be managed, since signal re-routing is localized at the nodes adjacent to the failure, the protection operations have to be performed on the entire set of wavelengths of the multiplex section (as described for SDH in ITU-T Recommendation G-803 and G-841) and the reconfigured nodes must re-route all the working channels previously sent on the damaged ring segment to their respective protection channels running onto the complementary ring arc. This technique is then identifiable as an "Optical Multiplex Section Shared Protection" technique. Thence, each node in the network must be equipped with the optical switching tools for the complete set of wavelengths in the ring, and a switch matrix is then needed with a complexity which increases considerably with increasing the number of channels (e.g. if each channel carries 2.5 Gb/s and the system is adapted to transmit 16

channels, each matrix must be able to switch 16×2.5 Gb/s). It can be demonstrated that, in this case, the required optical switching blocks to protect a number of links between N and $MN/2$ (where N is the number of wavelengths and M the number of nodes) is always MN .

5 Furthermore, the Applicant observes that, in the Optical Multiplex Section Shared Protection, since the failure control is performed at the multiplex section level, a failure on a single optical channel (e.g. when a node transmitter is damaged) can be either ignored or it can cause the reconfiguration of all the traffic thus causing a temporary failure on all the other working channels.

10 The Applicant further observes that, in case such a network is reconfigured as a consequence of a failure, the protection path of a generic optical channel may be longer than the maximum ring circumference. This can occur when a generic bidirectional link is set up between two non-adjacent nodes in the network, as illustrated in Figure 1a (where nodes A and D are involved). In case of failure the
15 switching action is performed by the two nodes adjacent to the failure (i.e. nodes B and C), as shown in Figure 1b. Briefly, each channel of the bidirectional link travels along the working path from the source node to one of the reconfigured nodes where it is routed into the protection path. Then it travels in opposite direction along all the ring network to the other reconfigured node where it is routed again on the working
20 path and, finally, it reaches the destination node. This alternative optical channel path may have a length exceeding the ring circumference, reaching values of several hundred ~~kilometers~~ kilometers and then introducing low levels of S/N ratio and high levels of attenuation. In case of a transoceanic application, this protection solution may lead, due to loopbacks, to restoration transmission paths that would
25 cross the ocean three times.

To overcome this last problem, a different protection solution has been proposed, which is referred to as a "MS shared protection ring - transoceanic application" in the Annex A of the Telecommunication standard ITU-T Recommendation G.841. In brief, a failure is detected at the two nodes adjacent to
30 the failure at the SDH multiplex section layer and, subsequently, the nodes terminating ~~failed~~ failed links are informed of the failure situation and re-route the corresponding links on the complementary ring arc path, as illustrated in Figure 1c.

In other words, in case of failure, all the transmission links affected by the failure are bridged at their source nodes onto the protection channels that travels away from the failure. When the affected links reach their final destination nodes, they are switched to their original drop point. Therefore, no loopbacks are established and there is no
5 risk of having, in case of failure, restoration transmission paths crossing more times the ocean.

The Applicant observed that, in this case, as in the protection solution of U.S. Patent No. 5,647,035, the failure control is over the entire optical multiplex section and, therefore, a failure on a single optical channel may be either ignored or it can
10 cause the reconfiguration of all the traffic thus causing a temporary failure on all the other working channels.

The Applicant further observes that a protection at the SDH layer requires a relatively complex electronic layout and can operate only at a predetermined bit rate.

SUMMARY OF THE INVENTION

The Applicant proposes, with the present invention, an improved type of shared protection technique, in which re-routing operations are performed only at the nodes which terminate affected links and only on the ~~failed~~ **failed** channels, thus avoiding the drawbacks related, to re-routing operations on the multiplex section, and by using an optical reconfigurable connection mechanism which allows the omission of a SDH layer protection mechanism. Moreover, the failure control is performed at the channel level instead of at the multiplex section level, thus avoiding the above mentioned drawbacks.

10 In the proposed network, the nodes communicate in pairs defining bidirectional links, and, under normal conditions, are optically configured so as to exchange signals on a respective working arc path at a respective first wavelength on a first carrier of the network and at a respective second wavelength on a second carrier of the network; in the complementary arc, the same wavelengths may be used
15 in the same manner to define other links, while the first wavelength on the second carrier and the second wavelength on the first carrier are reserved for protection and are used in case of failure affecting one of said links. Each node of the proposed network is provided with a pair of OADM (Optical Add/Drop Multiplexers) for extracting from, and inserting in, the optical multiplex section, only the channels
20 which the node is adapted to operate on. All the remaining channels are passed-through. Each node is further provided with a receiving/transmitting module for each pair of wavelengths defining a transmission link, said module optically connecting, in a selective way, the OADMs to optical transmitters and receivers operating at said wavelengths. Each receiving/transmitting module performs failure control and re-
25 routing operations on the two corresponding wavelengths. Consequently, in case of failure, if one of the links managed by this node is failed, the corresponding receiving/transmitting module, after detecting the failure by checking the channels status, is reconfigured in order to optically re-route the transmission on the complementary portion of the ring. The same operation is performed by the node at
30 the other end of the failed link. Therefore, only the nodes managing affected links are optically reconfigured and only the ~~failed~~ **failed** channels (instead of the global multiplex section) are re-routed.

The protection technique of the invention provides the following advantages:

- By operating protection at the channel level, it is possible to provide optical protection to a selected subset of optical channels and leave to other layers (e.g. SDH) or to other optical protection mechanisms the protection of the remaining
5 channels.

- Using an optical re-routing technique, it is possible to omit the SDH protection layer, thus simplifying the node structure and allowing a direct connection to the ring network for clients using different protocols (possibly unprotected) like ATM, IP, etc. The proposed protection technique is therefore compatible with every
10 client electronic transmission protocol.

- The receiving/transmitting module in the protection scheme of the invention includes an optical switching unit which, differently from SDH switching layouts, can operate at different bit rates (for example 155 Mbit/s, 622 Mbit/s, 2,5 Gbit/s, 10 Gbit/s)

15 - The protection technique of the invention allows a client to client protection, since a failure is detectable even if it affects a single channel, while generally the prior art techniques allow only global failure detection on the multiplexed flux (by using threshold photodiodes).

- The number of switching blocks is always two times the number of
20 protected channels (i.e. between $2N$ and MN , where N is the number of wavelengths and M the number of nodes) thus giving an advantage, with mixed traffic patterns, over the Optical Multiplex Section Shared Protection schema proposed in US 5,647,035. For example, with a typical 8 nodes, 32 wavelengths optical ring network ($M=8$, $N=32$), the required number of switching blocks for said Optical Multiplex
25 Section Shared Protection schema is always 256, while by using the Optical Channel Shared Protection schema of the invention the required number of switching blocks varies between 64 (in case of "hub traffic", i.e. one node communicating with all the other nodes) and 256 (in case of "uniform traffic", i.e. one node communicating only with its two adjacent nodes).

30 - Since the reconfiguration takes place at the channel level instead of at the multiplex section level as in US 5,647,035, it is no more needed to provide each node with a switching equipment to perform protection on all the network channels (in

particular it is then not necessary to use complex switch matrix as in the Optical Multiplex Section Shared Protection scheme).

- Differently from the Optical Multiplex Section Shared Protection scheme proposed in US 5,647,035, the complexity of the node switching structure depends
5 only on the number of links managed by the nodes and does not depend on the number of wavelengths in the network.

- Differently from the Optical Multiplex Section Shared Protection scheme proposed in US 5,647,035, switching operations are performed externally to the network, and then no transitories are present. In particular, switching of the single
10 channel is performed, as described below, between the receiving and the transmitting transponders and, therefore, the multiplexed optical flux conditions at the input of the node amplifier are substantially unchanged and then sudden power variations inside the network are avoided.

According to a first aspect, the present invention relates to an autoprotected
15 optical communication ring network, including a first and a second optical carrier having opposite transmission directions and a plurality of optically reconfigurable nodes optically connected along the first and the second optical carrier and adapted to communicate in pairs by means of respective links susceptible of failure, the ring network having a normal operative condition in which the nodes of each pair are
20 optically configured so as to exchange optical signals on a respective working arc path at a respective first wavelength on the first carrier and at a respective second wavelength different from said first wavelength on the second carrier, said respective working path having a complementary arc path defining a respective protection arc path in which the first wavelength on the first carrier and the second wavelength on
25 the second carrier can be used for further links and the first wavelength on the second carrier and the second wavelength on the first carrier are reserved for protection, wherein the ring network has a failure operative condition in which the nodes terminating a ~~failed~~ **failed** link are optically reconfigured so as to exchange optical signals on the respective protection arc path at the respective second
30 wavelength on the first carrier and at the respective first wavelength on the second carrier.

Preferably, each of said plurality of reconfigurable nodes is adapted to manage a predetermined subset of wavelengths within a set of transmission wavelengths and includes a first and a second optical add/drop multiplexer serially connected to said first and, respectively, second carrier to feed/extract said subset of wavelengths to/from said first and, respectively, second carrier, and to pass-through the remaining wavelengths of the set of transmission wavelengths.

Each of said plurality of reconfigurable nodes preferably includes at least a signal input, at least a signal output and a reconfigurable optical switch unit selectively coupling said at least an signal input and said at least a signal output to said first and second carriers.

Said at least a signal input may be optically coupled to a respective optical transmitter and said at least a signal output may be optically coupled to a respective optical receiver.

Each of said plurality of reconfigurable nodes may include information insertion devices selectively optically connectable to said at least a signal input and adapted to insert ~~signalling~~ signaling information into the optical signals and information extraction devices selectively optically connectable to said at least a signal output and adapted to extract ~~signalling~~ signaling information from the optical signals.

Said information insertion. devices and said information extraction devices may include optical transponders optically coupling said optical switch unit to said first and second carrier and adapted to change the signals wavelengths.

At least one of said reconfigurable nodes may include at least a first signal splitter adapted to receive a signal from either the first or the second carrier and to split said signal into a first and a second fraction which are sent towards a respective signal output and towards the same carrier, respectively.

Moreover, at least one of said reconfigurable nodes may include at least a second signal splitter optically coupled to a respective signal input and adapted to spit a signal coming from the respective signal input into a first and a second fraction which are sent towards the first carrier and the second carrier, respectively.

Said optical switch unit may include at least a first switch having a first input optically coupled to a respective signal input, a second input coupled to either the first or the second carrier and an output coupled the same carrier.

5 Said optical switch unit may further include at least a second switch having a first input coupled to the first carrier, a second input coupled the second carrier, and an output optically coupled to a respective signal output.

The present invention also relates to an optical transmission system including a first and a second ring network, each network including a first and a second optical carrier having opposite transmission directions and a plurality of optically reconfigurable nodes optically connected along the first and the second optical carrier and adapted to communicate in pairs by means of respective links susceptible of failure, each network having a normal operative condition in which the nodes of each pair are optically configured so as to exchange optical signals on a respective working arc path at a respective first wavelength on the first carrier and at a
10 respective second wavelength different from said first wavelength on the second carrier, said respective working path having a complementary arc path defining a respective protection arc path in which the first wavelength on the first carrier and the second wavelength on the second carrier can be used for further links and the first wavelength on the second carrier and the second wavelength on the first carrier are
15 reserved for protection, each network having a failure operative condition in which the nodes terminating a ~~failed~~ **failed** link are optically reconfigured so as to exchange optical signals on the respective protection arc path at the respective second wavelength on the first carrier and at the respective first wavelength on the second carrier, each of said plurality of reconfigurable nodes including at least a
20 signal input, at least a signal output and a reconfigurable optical switch unit selectively coupling said at least an signal input and said at least a signal output to said first and second carriers, wherein a first reconfigurable node of the first ring network has a signal input which is optically coupled to a signal output of a second reconfigurable node of the second ring network.

30 The second reconfigurable node preferably has a signal input which is optically coupled to a signal output of the first reconfigurable node.

Preferably, a third reconfigurable node of the first ring network has a signal input which is optically coupled to a signal output of a fourth ~~reconfigurable node~~ **reconfigurable** node of the second ring network, and the fourth reconfigurable node has a signal input which is optically coupled to a signal output of the third reconfigurable node.

According to a further aspect, the present invention relates to a method to autoprotect an optical ring network, said ring network including a first and a second optical carrier having opposite transmission directions and a plurality of nodes optically connected along the first and the second optical carrier and adapted to communicate in pairs in order to define bidirectional links, each pair including a first and a second link termination node adapted to mutually communicate at respective first and second wavelengths, the method including:

- exchanging signals between the first and the second link termination node of each pair on a. respective working arc path of said ring network by using the respective first wavelength on the first carrier and the respective second wavelength on the second carrier; said respective working path having a complementary arc path defining a respective protection arc path in which the first wavelength on the first carrier and the second wavelength on the second carrier can be used for further links and the first wavelength on the second carrier and the second wavelength on the first carrier are reserved for protection;
- checking if a failure is present in the ring network producing at least a ~~failed~~ **failed** link; and
- optically reconfiguring, in the presence of a failure, the link terminating nodes of said at least a ~~failed~~ **failed** link so that they exchange signals on the respective protection arc path by using the respective first wavelength on the second carrier and the respective first wavelength on the second carrier.

Preferably, each node of said plurality of nodes is adapted to manage a predetermined subset of wavelengths within a set of transmission wavelengths carried by the first and the second carrier, said step of exchanging including optically separating, at each node of said plurality of nodes, each wavelength of the respective subset of wavelengths from the set of transmission wavelengths.

Preferably, the method includes the steps of inputting a signal into one of said nodes, splitting said signal into a first and a second fraction and sending said first fraction towards the first carrier and the second power fraction towards the second carrier.

5 Moreover, the method preferably includes the steps of receiving a signal in one of said nodes from either the first or the second carrier, splitting said signal into a first and a second fraction, sending the first fraction towards the same carrier and the second fraction towards a signal output of said node.

10 The step of checking may include verifying, in each node of said plurality of nodes and for each wavelength of the respective set of wavelengths, if signals are received.

The step of checking may include verifying, in each node of said plurality of nodes and for each wavelength of the respective set of wavelengths, if signals are received degraded.

15 The step of checking may include verifying, in each node of said plurality of nodes and for each wavelength of the respective set of wavelengths, if signals include a failure message.

20 The method may further include transmitting a failure message from a first link termination node of a pair to a second link termination node of the same pair if a signal transmitted from the second link termination node to the first link termination node is not received, or is received degraded, by the first link termination node.

Advantageously, the step of reconfiguring includes switching optical connections which selectively couple at least an optical transmitter and an optical receiver to said first and second carrier.

25 Preferably, the step of exchanging includes feeding at each of said plurality of nodes the corresponding subset of wavelengths to said first and, respectively, second carrier.

The step of exchanging signals may include the following steps executed in the first link termination node of a pair:

- 30 -
- generating an optical signal carrying an information;
 - converting the optical signal [[in a]] into an electrical signal;
 - adding to the electrical signal further information;

- reconverting the electrical signal [[in]] into an optical signal provided with a predetermined wavelength adapted for transmission; and
- feeding the optical signal at the predetermined wavelength to either the first or the second carrier;

5 and the following steps executed in the second link termination node of the same pair:

- receiving the optical signal at the predetermined wavelength from either the first or the second carrier;
- converting the optical signal at the predetermined wavelength [[in]] into an electrical signal;
- 10 - extracting from the electrical signal the further information;
- reconverting the electrical signal [[in]] into an optical signal with a wavelength adapted for reception; and
- receiving the optical signal with the wavelength adapted for reception.

15 According to a further aspect, the present invention relates to a reconfigurable node for an autoprotected optical communication ring network, comprising a receiving/transmitting module including:

- a signal input for the insertion into the node of a signal including information to be transmitted in the network;
- 20 - a signal output for the extraction from the node of a signal including information transmitted in the network;
- a first transmitting transponder for optically coupling to a first carrier of the network and adapted to modulate a signal at a first wavelength;
- a second transmitting transponder for optically coupling to the first carrier and adapted to modulate a signal at a second wavelength;
- 25 - a third transmitting transponder for optically coupling to a second carrier of the network and adapted to modulate a signal at the first wavelength;
- a first receiving transponder for optically coupling to the second carrier and adapted to demodulate a signal having the first wavelength;
- 30 - a second receiving transponder for optically coupling to the [[first]] second carrier and adapted to demodulate a signal having the ~~second~~ first wavelength;

- a third receiving transponder for optically coupling to the second carrier and adapted to demodulate a signal having the second wavelength;
 - ~~reconfigurable~~ **reconfigurable** optical connections to selectively connect:
 - the signal input either to the first transmitting transponder or to the third transmitting transponder;
 - the first receiving transponder to the third transmitting transponder;
 - the second receiving transponder to the signal output; and
 - the third receiving transponder either to the signal output or to the second transmitting transponder.
- 10 The receiving/transmitting module may further include:
- a further signal input for the insertion into the node of a signal including information to be transmitted in the network;
 - a further signal output for the extraction from the node of a signal including information transmitted in the network;
- 15 - a fourth transmitting transponder optically coupled to the second carrier and adapted to modulate a signal at the second wavelength; and
- a fourth receiving transponder optically coupled to the first carrier and adapted to demodulate a signal having the first wavelength;
- said reconfigurable optical connections selectively connecting:
- 20
- the first receiving transponder either to the third transmitting transponder or to the further signal output;
 - the fourth receiving transponder to the further signal output; and
 - the further signal input either to the second transmitting transponder or to the fourth transmitting transponder.
- 25 Preferably, the node is adapted to manage a predetermined set of wavelengths within a set of transmission wavelengths including a first and a second optical add/drop multiplexer optically coupling the receiving/transmitting module to said first and, respectively, second carrier to feed/extract said subset of wavelengths to/from said first and, respectively, second carrier, and to pass-through the remaining
- 30 wavelengths of the set of transmission wavelengths.
- The node according may further include at least a first optical power splitter for splitting signals coming from said at least a signal input and at least a second

optical power splitter for splitting signals coming from a respective one of said receiving transponders.

The reconfigurable optical connections may include 2x2 switches or, alternatively, 1x2 and/or 2x1 switches.

5 The reconfigurable optical connections may include discrete switching components or, alternatively, an integrated switching matrix.

The reconfigurable optical connections may include optical switching components selectable in the group including:

- opto-mechanical switches;
- 10 - thermo-optical switches;
- magneto-optical switches;
- liquid crystal switches;
- semiconductor switches;
- electro-optical switches;
- 15 - micro-mechanical switches; and
- lithium niobate integrated circuit switches

The reconfigurable node preferably includes a control processing unit operatively connected to said receiving transponders and said transmitting transponders.

20 The reconfigurable node may includes at least a further receiving/transmitting module which has substantially the same structure of said receiving/transmitting module and is adapted to operate with a different pair of wavelengths with respect to said receiving/transmitting module.

BRIEF DESCRIPTION OF THE DRAWINGS

More details will become apparent from the following description, with reference to the accompanying drawings, in which:

5 Figures 1a, 1b, 1c show a network ring of a known. type under normal conditions, failure condition with a multiplex section shared protection and failure condition with a multiplex section shared protection - transoceanic application.

Figure 2 is a schematic representation of an optical communication network according to the present invention, operating under normal conditions and in which, by way of example, two transmission links are defined;

10 Figure 3 is a more detailed representation of one node of the network of Figure 2, including a switching unit comprising 2x2 switches and operating under normal conditions;

Figure 4 shows a switching unit comprising 1x2 and 2x1 switches used in the network of Figure 2 in place of the switching unit comprising 2x2 switches, operating under normal conditions;

Figure 5 shows a switching unit comprising an integrated switching circuit used in the network of Figure 2 in place of the switching unit comprising 2x2 switches, operating under normal conditions;

20 Figure 6 illustrates a sub-equipped node for the network of Figure 2, adapted to manage only one transmission link and including 2x2 switches;

Figure 7 shows a switching unit comprising 1x2 and 2x1 switches used in the network of Figure 6 in place of the switching unit comprising 2x2 switches, under normal operative conditions;

25 Figure 8 shows a switching unit comprising an integrated switching circuit used in the network of Figure 6 in place of the switching unit comprising 2x2 switches, under normal operative conditions;

Figure 9 illustrates the network of Figure 2 under a failure condition;

Figure 10 shows the reconfiguration of the node of Figure 3 when a failure occurs on its left-hand side;

30 Figure 11 shows the reconfiguration of the switching unit of Figure 4 when a failure occurs on the left-hand side of the node;

Figure 12 shows the reconfiguration of the switching unit of Figure 5 when a failure occurs on the left-hand side of the node;

Figure 13 shows the reconfiguration of the node of Figure 3 when a failure occurs on its right-hand side;

5 Figure 14 shows the reconfiguration of the switching unit of Figure 4 when a failure occurs on the right-hand side of the node;

Figure 15 shows the reconfiguration of the switching unit of Figure 5 when a failure occurs on the right-hand side of the node;

Figure 16 illustrates an alternative node architecture;

10 Figures 17 is a schematic representation of signal routing in the node of Figure 16 under normal operative conditions;

Figure 18 shows the reconfiguration of the node of Figure 16 when a failure occurs on its left-hand side;

15 Figure 19 illustrates schematically signal routing in the node of Figure 16 when multicasting/broadcasting of working channels is performed;

Figure 20 illustrates schematically signal routing in the node of Figure 16 when multicasting/broadcasting of protection channels is performed; and

Figures 21-24 illustrate signal exchange between two different ring network under normal operative conditions and for different failure conditions.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Schematically shown in Figure 2 is an optical communication ring network 1 according to the present invention. NetWork 1 includes a first and a second optical [[fibre]] **fiber** ring 2, 3 defining respective optical carriers having opposite
5 transmission directions, and a plurality of nodes 20a-20f for adding and dropping optical signals, positioned along the first and the second ring 2, 3.

Network 1 is adapted to be used for. both terrestrial transmissions and transoceanic transmissions. For long-haul transmissions, in particular for transoceanic transmissions, network 1 is preferably provided with line optical
10 amplifiers and/or boosters and/or preamplifiers (not shown).

In the schematic representation of Figure 2, rings 2, 3 define an external and, respectively, an internal ring, having a counter-clockwise transmission direction and, respectively, a clockwise transmission direction. The nodes in network 1 have been chosen in number of six just by way of example and the present invention is
15 identically applicable to networks including any number of nodes. Furthermore, the reference to connections comprising two optical fibers is to be considered merely as an example, the solution according to the invention being also suitable for utilization in ring networks in which the nodes are connected by a greater number of optical carriers.

20 Communication in network 1 is achieved according to a Wavelength Division Multiplexing (WDM) scheme using different channels at respective wavelengths on each ring. In particular, rings 2, 3 are adapted to convey optical signals in the transmission channels defined by a set of transmission wavelengths $\lambda_1, \lambda_2, \dots, \lambda_n$ within a predetermined wavelength transmission band.

25 Each of the nodes 20a-20f is adapted to manage a respective subset of wavelengths within the set of transmission wavelengths $\lambda_1, \lambda_2, \dots, \lambda_n$ and to define bidirectional communications with one or more of the other nodes of network 1. Each pair of nodes arranged to mutually communicate splits network 1 into two complementary arc paths, at least one of which (identifiable as a "working path")
30 allows bidirectional transmission between the two nodes under normal operative conditions (i.e. without failures), and the other (identifiable as a "protection path")

allows to re-route such bidirectional transmission in the presence of a failure in the working path.

In greater detail, a generic pair of nodes arranged to mutually communicate has associated respective first and second wavelengths λ_x, λ_y for the exchange of data. Under normal operative conditions, on the working path defined by the considered pair of nodes, a bi-directional working link is established by transmitting optical signals at the first wavelength λ_x on the external ring 2 (in the counter-clockwise direction) and at the second wavelength λ_y on the internal ring 3 (in the clockwise direction). The second wavelength λ_y is not used on the external ring 2 and the first wavelength λ_x is not used on the internal ring 3. The second wavelength λ_y and the first wavelength λ_x can then be used on the external ring 2 and, respectively, on the internal ring 3, to provide optical protection, as hereinbelow described. For aim of clarity, the wavelengths which are used under normal operative conditions (i.e. λ_x on the ~~external~~ **external** ring 2 and λ_y on the internal ring 3) to perform working links are identified with a "w" suffix ($\lambda_{x,w}, \lambda_{y,w}$), while the wavelengths which are adapted to be used for protection (i.e. λ_y on the ~~external~~ **external** ring 2 and λ_x on the internal ring 3) are identified with a "p" suffix ($\lambda_{x,p}, \lambda_{y,p}$).

The first and the second wavelength λ_x, λ_y can be used on the protection path associated to the considered pair of nodes to perform a further bidirectional working link between the first and the second node or to perform further bidirectional working links between other pairs of nodes (which may include one of the previously considered nodes), provided that those further working links do not overlap with each other and with the above considered one. Then, a generic pair of wavelengths λ_x, λ_y defines a "logical ring", i.e. a virtual ring which may include many non-overlapping working links operating at $\lambda_{x,w}, \lambda_{y,w}$. Protection wavelengths $\lambda_{x,p}, \lambda_{y,p}$, not used under normal operative conditions, are shared among the different working links

operating at $\lambda_{x,w}$, $\lambda_{y,w}$, (i.e. on the same logical ring). Overlapping working links can only be part of different logical rings and operate at different wavelengths.

The number of working links in a single logic ring depends on the client traffic pattern. For example with M nodes and N wavelengths (N even), in case of "hub traffic" (i.e. one node communicating with all the other nodes) a maximum of N protected working links can be established because each logical ring can support only two working links, while in case of "uniform traffic" (i.e. each node communicating only with its two adjacent) a maximum of MN/2 protected working links are available because each logical ring (i.e. each pair of wavelengths) can support M working links.

In the example of Figure 2, one working link is set up between node 20c and node 20f using the first working wavelength $\lambda_{x,w}$ on the external ring 2 and the second working wavelength $\lambda_{y,w}$ on the internal ring 3. Another working link is set up with the same wavelengths (and directions of propagation on the two rings 2, 3) between node 20d and node 20e. In this example, it is also possible to use the same wavelengths to set up a working link between node 20c and node 20d and between node 20e and node 20f, but it is not possible for example to set up a working link between node 20b and node 20e because it will overlap with the ring arcs already used by the previous links..

As later described in greater detail, each of nodes 20a-20f provides optical add/drop/bypass functions for each wavelength within the wavelength transmission band on both the external and internal fiber rings 2, 3, together with optical amplification and regeneration (if necessary).

Figure 3 shows the structure of a generic node 20i of network 1, in particular of one node operating at wavelengths λ_x and λ_y .

Node 20i includes a first and a second optical add/drop multiplexer (OADM) 4, 5 and a receiving/transmitting module 6 comprising:

- a first and a second signal input IN_1 , IN_2 ;
- a first and a second signal output OUT_1 , OUT_2 ;
- a first, a second, a third and a fourth transmitting transponder $TxT_1(\lambda_x)$, $TxT_1(\lambda_y)$, $TxT_2(\lambda_x)$, $TxT_2(\lambda_y)$;

- a first, a second, a third and a fourth receiving transponder $RxT_1(\lambda_x)$, $RxT_1(\lambda_y)$, $RxT_2(\lambda_x)$, $RxT_2(\lambda_y)$;
- a switch unit 15; and
- a central processing unit (CPU) 16.

5 The first and the second OADM 4, 5 are adapted to insert into rings 2, 3, and to extract from rings 2, 3, signals at the working and protection wavelengths associated to node 20i (i.e. λ_x and λ_y) and to by-pass the other wavelengths of the set of transmission wavelengths. If required, OADMs 4, 5 may perform other functions within the wavelength transmission band, such as regeneration,
10 performance monitoring, etc. In greater detail, the first OADM 4 is coupled to the fiber of the external ring 2 for dropping signals from, and adding signals into, the external ring 2, and the second OADM 5 is coupled to the fiber of the internal ring 3 for dropping signals from, and adding signals into, the internal ring 3. OADMs 4 and 5 may be, for example, of the type Pirelli Optical Systems OADM/P4-R1
15 (WaveMux6400 product family).

Inputs IN_1 , IN_2 and outputs OUT_1 , OUT_2 represent the client access points for the input and the output of information. Inputs IN_1 , IN_2 can be optical coupled to optical transmitters Tx_1 , Tx_2 and outputs OUT_1 , OUT_2 can be optical coupled to optical receivers Rx_1 , Rx_2 , as illustrated in Figure 3. Transmitters Tx_1 , Tx_2 allow the
20 input of information addressed to two different receivers connected to network 1. The input of information by transmitters Tx_1 , Tx_2 may be performed at wavelengths not included in the transmission wavelength band of network 1, since the transmitting transponders $TxTs$ are in charge to provide the signals with the correct wavelength, i.e. with the first wavelength λ_x or the second wavelength λ_y . Tx_1 , Tx_2 may be, for
25 example, for example a standard Sonet OC-48/SDH STM-16 terminal (produced for example by Nortel). Different bit rate terminals can be used provided that the transmitting transponders are compatible.

Receivers Rx_1 , Rx_2 allow the output of information coming from two different transmitters connected to network 1. Receivers Rx_1 , Rx_2 may be adapted to
30 receive signals at wavelengths not included in the transmission wavelength band of network 1, since receiving transponders $RxTs$ are in charge to provide the signals

coming from the network 1 with a wavelength adapted for reception receivers Rx₁, Rx₂. Rx₁, Rx₂ may be, for example, a standard Sonet OC-48/SDH STM-16 terminal (produced for example by Nortel). Different bit rate terminals can be used provided that the receiving transponders are compatible.

5 The first and the second transmitting transponder TxT₁(λ_x), TxT₁(λ_y) are optically coupled to the external ring 2 by means of the first OADM 4 and are adapted to feed signals at wavelength λ_x and, respectively, λ_y , to the external ring 2; the third and the fourth transmitting transponder TxT₂(λ_x), TxT₂(λ_y) are optically coupled to the internal ring 3 by means of the second OADM 5 and are
10 adapted to feed signals at wavelength λ_x and, respectively, λ_y , to the internal ring 3.

 In detail, each transmitting transponder TxT₁(λ_x), TxT₁(λ_y), TxT₂(λ_x), TxT₂(λ_y) may be of a type adapted to receive an optical signal from switch unit 15, to transform it into electrical format for processing and to newly transform it into optical format for transmission, with a predetermined wavelength within the wavelength band. Transmitting transponders of this type are, for example, Pirelli
15 Optical Systems WCM/F-xxx (WaveMux6400 product family, xxx = output wavelength code). Alternatively, the transmitting transponder may be completely optical devices (for example based on SOAs, Semiconductor Optical Amplifiers) managing information associated to the signal, for example managing a pilot tone
20 over-modulating the optical wavelength carrying the signal.

 Processing, in this case, includes providing the transmitted signals with information for protection purposes (e.g. channel identifier, performance monitoring, protection protocol) as a channel overhead. This information is not part of the client payload and are added to the signal by the transmitting transponders under the
25 supervision of the CPU. For example the Pirelli Optical Systems WCM/F-xxx unit is able to add an overhead. channel to the client payload to transport the ~~signalling~~ **signaling** information. A similar technique, but operating at the multiplex section level, is used in the Sonet/SDH protocol at the transmitting side (e.g. channel overhead, multiplex section overhead with B1 monitor byte and K1/K2 APS bytes).

The first and the second receiving transponder $RxT_1(\lambda_x)$, $RxT_1(\lambda_y)$ are optically coupled to the external ring 2 by means of the first OAOM 4 and are adapted to receive signals at wavelength λ_x and, respectively, λ_y ; the third and the fourth receiving transponder $RxT_2(\lambda_x)$, $RxT_2(\lambda_y)$ are optically coupled to the internal ring 3 by means of the second OADM 5 and are adapted to receive signals at wavelength λ_x and, respectively, λ_y .

In detail, each receiving transponder $RxT_1(\lambda_x)$, $RxT_1(\lambda_y)$, $RxT_2(\lambda_x)$, $RxT_2(\lambda_y)$ may be of the type adapted to receive an optical signal from rings 2, 3, to transform it into electrical format for processing and to newly transform it into optical format, with a predetermined wavelength adapted for reception by a corresponding receiver Rx_1 , Rx_2 . Receiving transponders of this type are, for example, Pirelli Optical Systems RXT-DM/F (WaveMux6400 product family). Alternatively, the receiving transponders, like the transmitting transponders, may be completely optical devices (for example based on SOAs, Semiconductor Optical Amplifiers) managing information associated to the signal, for example to a pilot tone over-modulating the optical wavelength carrying the signal.

Processing, in this case, includes extracting from the received signals the information previously inserted as channel overhead by the corresponding TXT at the transmitting node for protection purposes (e.g. channel identifier, performance monitoring, protection protocol). For example the Pirelli Optical Systems RXT-DM/F unit is able to extract an overhead channel from the received signal to process the ~~signalling~~ **signaling** information. A similar technique, but operating at the multiplex section level, is used in the Sonet/SDH protocol at the receiving side (e.g. channel overhead, multiplex section overhead with B1 monitor byte and K1/K2 APS bytes).

CPU 16 is in charge to communicate with the transmitting and receiving transponders TxTs, RxTs in order to provide or to process the information related to the working links (link ~~signalling~~ **signaling**), to check the operative conditions of the related working links and to control switch unit 15 in accordance to the detected operative conditions. Link ~~signalling~~ **signaling** must include channel identification

information which can be implemented for example either by means of a pilot tone over-modulating the optical wavelength carrying the signal or by using a TDM (Time Division Multiplexing) frame structure including the signal channels together with an extra channel for link ~~signalling~~ signaling transmission. Logical connections
5 between CPU 16 and its controlled units are represented in Figure 3 by means of dashed lines.

Switch unit 15 is adapted to provide the optical switching facilities implementing the protection layout as disclosed in this invention, by selectively connecting transmitters TxS and receivers RxS to transmitting transponders TxTs and
10 receiving transponders RxTs. As shown in Figure 3, switch unit 15 may comprise a first, a second, a third and a fourth 2x2 optical switch 22-25 driven by CPU 16 through appropriate control logics (not shown). Optical switches 22-25 may be, for example, 2x2 optomechanical switches (e.g. of the type produced by JDS FITELE, INC., 570 Heston Drive, Nepean, Ontario (CA) or of the type produced by E-TEK
15 DYNAMICS, INC., 1885 Lundy Ave., San Jose, CA (USA)). Optical switches 22-25 are connected as follows:

- the first switch 22 has a first input 22a coupled to the first transmitter TX₁ via the first signal input IN₁, a second input 22b, a first output 22c coupled to the first transmitting transponder TxT₁(λ_x) and a second output 22d coupled to
20 the third transmitting transponder TxT₂(λ_x);
- the second switch 23 has a first input 23a coupled to the fourth receiving transponder RxT₂(λ_y), a second input 23b coupled to the second receiving transponder RxT₁(λ_y), a first output 23c coupled to the first receiver Rx₁ via the first signal output OUT₁, and a second output 23d;
- 25 - the third switch 24 has a first input 24a coupled to the second output 23d of the second switch 23, a second input 24b coupled to the second transmitter TX₂ via the second signal input IN₂, a first output 24c coupled to the second transmitting transponder TxT₁(λ_y) and a second output 24d coupled to the fourth transmitting transponder TxT₂(λ_y); and

- the fourth switch 25 has a first input 25a coupled to the third receiving transponder $RxT_2(\lambda_x)$, a second input 25b coupled to the first receiving transponder $RxT_1(\lambda_x)$, a first output 25c coupled to the second input 22b of the first switch 22 and a second output 25d coupled to the second receiver Rx_2 via the second signal output OUT_2 .

Each switch 22-25 can operate in a bypass status (typically used under normal conditions), in which the first input is coupled to the first output and the second input is coupled to the second output, or in a switched status (typically used in case of failure), in which the first input is coupled to the second output and the second input is coupled to the first output.

The architecture of Figure 3 is modular and can be applied for each logical ring in which the node acts as a link termination. In other words, node 20i may include a plurality of modules 6, each for managing a different pair of wavelength. In this case, the wavelengths assigned to each logical ring are separately added/dropped by the two OADMs 4, 5 and processed separately by a corresponding module 6.

It has to be noted that the functional layout of the node described above can be physically implemented in different ways, for example integrating the CPU 16 or the transponders 6-13 inside the switch unit 15.

[[Swich]] **Switch** unit 15 is over-dimensioned for the switching requirements of node 20I and it defines, in case of failure, some interconnections which are not operatively used. For example, while the first receiving transponder $RxT_1(\lambda_x)$ is connected to the second receiver Rx_2 under normal operative conditions, no connection is needed for the first receiving transponder $RxT_1(\lambda_x)$ in case of failure on the external ring 2 on the right-hand side of node 20i (since no signal is received from this side). Taking into consideration this over-dimensioning of the switch unit functionality, it is possible to use, in place of the 2x2 switch type unit, other unit architectures which allow to optimize the number of interconnections in relation to the functional requirements. The interconnection requirements in node 20i under both normal and failure conditions (i.e. for working and protection) is summarized in the following table:

	Rx ₁	Rx ₂	TXT ₁ (λ_x)	TXT ₁ (λ_y)	TXT ₂ (λ_x)	TXT ₂ (λ_y)
TX ₁			W		P	
TX ₂				P		W
RXT ₁ (λ_x)		W				
RXT ₁ (λ_y)	P			P		
RXT ₂ (λ_x)		P			P	
RXT ₂ (λ_y)	W					

W=Working

P=Protection

Figure 4 shows a switch unit 15' including 1x2 and 2x1 optomechanical switches, to be used in place of switch unit 15. Switch unit 15' implements the required interconnection functionality and can be, for example, of the type produced by JDS FITELE, INC., 570 Heston Drive, Nepean, Ontario (CA) or of the type produced by E-TEK DYNAMICS, INC., 1885 Lundy Ave., San Jose, CA (USA). In Figure 4, for reason of clarity, the input connections and the output connections of switch, unit 15' are grouped on the left side and, respectively, on the right side of switch unit 15'. In detail, switch unit 15' include:

- a first switch 31 of the 1x2 type, having its input coupled to the first transmitter TX₁ (via the first signal input IN₁), and its first output coupled to the first transmitting transponder TxT₁(λ_x);
- 15 - a second switch 32 of the 2x1 type, having its first input coupled to the second output of the first switch 31 and its output coupled to the third transmitting transponder TxT₂(λ_x);
- a third switch 33 of the 1x2 type, having its input coupled to the third receiving transponder RxT₂(λ_x) and its first output coupled to the second
- 20 input of the second switch 32;
- a fourth switch 34 of the 2x1 type, having its first input coupled to the second output of the third switch 33, its second input coupled to the first receiving

transponder $RxT_1(\lambda_x)$ and its output coupled to the second receiver Rx_2 (via the second signal output OUT_2);

- a fifth switch 35 of the 2x1 type, having its first input coupled to the fourth receiving transponder $RxT_2(\lambda_y)$ and its output coupled to the first receiver Rx_1 (via the first signal output OUT_1);
- a sixth switch 36 of the 1x2 type, having its input coupled to the second receiving transponder $RxT_1(\lambda_y)$ and a first output coupled to the second input of the fifth switch 35;
- a seventh switch 37 of the 2x1 type, having its first input coupled to the second output of the sixth switch 36 and its output coupled to the second transmitting transponder $TxT_1(\lambda_y)$; and
- an eighth switch 38 of the 1x2 type, having its input coupled to the second transmitter TX_2 (via the second signal input IN_2), its first output coupled to the second input of the seventh switch 37 and its second output coupled to the fourth transmitting transponder $TxT_2(\lambda_y)$.

In Figure 4, connections which are operative under normal conditions are shown with a continuous line, while connections which are not used under normal conditions are represented with a dashed line.

In a further possible embodiment shown in Figure 5, the switch unit, here indicated with 15", includes a lithium niobate ($LiNbO_3$) integrated switching matrix, in which interconnections among input and outputs reproduce the layout of the switch unit 15' of Figure 4. In particular, switch unit 15" includes four 1x2 switches each comprising:

- an input waveguide,
 - a Y-shaped branching waveguide having one input arm connected to input waveguide and having two output arms, and
 - a first and a second output waveguides each connected to one of the output arms of the branching waveguide,
- and four 2x1 switches each comprising:
- a first and a second input waveguide,

- a Y-shaped branching waveguide having two. input arms connected to the input waveguide and one output arm, and
- a first output waveguide connected to the output arm of the branching waveguide.

5 Switch unit 15" also includes electrodes (not shown) formed on the surface of substrate in correspondence of the Y-shaped branching waveguides and adapted to produce the switching action between the two arms of the Y.

In detail, switch unit 15" includes:

- 10 - a first switch 41 (1x2) having its input waveguide coupled to the first transmitter TX_1 (via the first signal input IN_1) and its first output waveguide coupled to the first transmitting transponder $TxT_1(\lambda_x)$;
- a second switch 42 (2x1) having its first input waveguide coupled to the second output waveguide of the first switch 41 and its output waveguide coupled to the third transmitting transponder $TxT_2(\lambda_x)$;
- 15 - a third switch 43 (1x2) having its input waveguide coupled to the third receiving transponder $RxT_2(\lambda_x)$ and its first output waveguide coupled to the second input waveguide of the second switch 42;
- a fourth switch 44 (2x1) having its first input waveguide coupled to the second output waveguide of the third switch 43, its second input waveguide coupled to the first receiving transponder $RxT_1(\lambda_x)$ and its output waveguide coupled to the second receiver Rx_2 (via the second signal output OUT_2);
- 20 - a fifth switch 45 (2x1) having its first input waveguide coupled to the fourth receiving transponder $RxT_2(\lambda_y)$ and its output waveguide coupled to the first receiver Rx_1 (via the first signal output OUT_1);
- 25 - a sixth switch 46 (1x2) having its input waveguide coupled to the second receiving transponder $RxT_1(\lambda_y)$ and its first output waveguide coupled to the second input waveguide of the fifth switch 45;
- a seventh switch 47 (2x1) having a first input waveguide coupled to the second output waveguide of the sixth switch 46 and an output waveguide coupled to the second transmitting transponder $TxT_1(\lambda_y)$; and
- 30

- an eighth switch 48 (1x2) having an input waveguide coupled to the second transmitter TX₂ (via the second signal input IN₂), a first output waveguide coupled to the second input waveguide of the seventh switch 47 and a second output waveguide coupled to the fourth transmitting transponder TxT₂(λ_y).

5 In Figure 5, connections which are operative under normal conditions are shown with a continuous line, while connections which are not used under normal conditions are represented with a dashed line.

The use of an integrated switching matrix offers several advantages over a discrete components switching matrix. In particular:

- 10 - opto-mechanical switch units 15 and 15' are more cumbersome than the integrated switch unit 15"; for example, a typical 2x2 opto-mechanical switch may occupy a surface of about 48x18 mm², and four switches are needed to form the switch unit 15, while the integrated switch unit 15" may occupy an area of about 4x65 mm²;
- 15 - integrated switch unit 15" has response times lower than opto-mechanical switch units 15 and 15'; in fact, integrated switch unit 15" allows response times of about 1 ms, while opto-mechanical switch units 15 and 15' have typical response times of about 5-10 ms;
- the use of a single integrated device in place of four 2x2 switches or eight 1x2 and 2x1 switches allows to simplify the piloting electronic circuit;
- 20 - integrated switch unit 15" is cheaper than opto-mechanical switch units 15 and 15'.

Alternatively to the optomechanical switch units 15 and 15' and to the lithium niobate integrated switch unit 15", other types of optical switch units may be used, including either a discrete components switching matrix or an integrated switching matrix, for example including thermo-optical switches, magneto-optical switches, liquid crystal switches, SOA (Semiconductor Optical Amplifier) switches, electro-optical switches and micro-mechanical switches (MEMS).

The node structure previously described is adapted to manage two working links on the same logical ring. Anyway, if the client traffic pattern requires only one working link to be terminated at a generic node, this node may be sub-equipped. This situation is depicted in Figure 6, where a generic one-link node 20j adapted to

manage a single working link in its left-hand side is shown under normal operative conditions.

Node 20j differs from the node 20i of Figure 3 in that the second signal input IN_2 , the second transmitter TX_2 , the second signal output OUT_2 , the second receiver Rx_2 the first receiving transponder $RxT_1(\lambda_x)$ and the fourth transmitting transponder $TxT_2(\lambda_y)$ of node 20i are absent, and in that it includes a switch unit 115 which does not comprise the third and the fourth switch 24, 25 of switch unit 15. Therefore, differently from the architecture of Figure 3, the third receiving transponder $RxT_2(\lambda_x)$ is directly coupled to the second input 22b of the first switch 22 and the second output 23d of the second switch 23 is directly coupled to the second transmitting transponder $TxT_1(\lambda_y)$. The single working link managed by node 20j includes signals sent by node 20j to another node at the working wavelength $\lambda_{x,w}$ on the external ring 2 and signals received by node 20j from the other node at the working wavelength $\lambda_{y,w}$ on the internal ring 3. Protection wavelengths $\lambda_{x,p}$ and $\lambda_{y,p}$ are managed in the same way as described before for the two-link node.

Figure 7 shows an alternative switch unit 115' for a one-link node to be used in place of switch unit 115. Switch unit 115' includes 1x2 and 2x1 optomechanical switches of the same type as those of switch unit 15' and implements the interconnection functionality required for node 20j, omitting the unused interconnections. For sake of clarity, input connections and output connections of switch unit 115' are grouped on the left side and, respectively, on the right side of switch unit 115'.

Switch unit 115' includes a first switch 131 (1x2), a second switch 132 (2x1), a third switch 135 (2x1) and a fourth switch 136 (1x2) respectively equivalent to switches 31, 32, 35 and 36 of switch unit 15' (Figure 4) and differs from switch unit 15' in that switches 33, 34, 37 and 38 of switch unit 15' are absent.

In detail, switch unit 115' include:

- a first switch 131 of the 1x2 type, having its input coupled to the first transmitter TX_1 via the first signal input IN_1 and its first output coupled to the first transmitting transponder $TxT_1(\lambda_x)$;
- a second switch 132 of the 2x1 type, having its first input coupled to the second output of the first switch 131, its second input coupled to the third

receiving transponder $RxT_2(\lambda_x)$ and its output coupled to the third transmitting transponder $TxT_2(\lambda_x)$;

- a third switch 135 of the 2x1 type, having its first input coupled to the fourth receiving transponder $RxT_2(\lambda_y)$ and its output coupled to the first receiver Rx_1 via the first signal output OUT_1 ; and
- a fourth switch 136 of the 1x2 type, having its input coupled to the second receiving transponder $RxT_1(\lambda_y)$, a first output coupled to the second input of the third switch 135 and a second output coupled to the second transmitting transponder $TxT_1(\lambda_y)$.

In Figure 7, connections which are operative under normal conditions are shown with a continuous line, while connections which are not used under normal conditions are represented with a dashed line.

Figure 8 shows an integrated optics switch unit 115" having the same switching architecture of switch unit 115' of Figure 7, but realized using the same technology of switch unit 15" of Figure 5, i.e. lithium niobate ($LiNbO_3$) integrated circuit technology. Switch unit 115" includes a first switch 141 (1x2), a second switch 142 (2x1), a third switch 145 (2x1) and a fourth switch 146 (1x2) performing the same signal routing as the corresponding switches of switch unit 115' (figure 7).

Alternatively, switch units 115, 115' and 115" may include switches selectable in the set comprising thermo-optical switches, magneto-optical switches, liquid crystal switches, SOA (Semiconductor Optical Amplifier) switches, electro-optical switches, and micro-mechanical switches (MEMS).

Network 1 operates as follows.

When a link between a first and a second node of the network 1 has to be established, a generic pair of first and second wavelengths λ_x, λ_y is chosen within the wavelength band. A working link is then set up between the two nodes by connecting the first transmitter Tx_1 of the first node to the second receiver Rx_2 of the second node using the first wavelength λ_x on the external ring 2, and by connecting the second transmitter Tx_2 of the second node to the first receiver Rx_1 of the first node using the second wavelength λ_y on the internal ring 3, on a same working arc path. As previously described, other working links may be set up in the protection path of the two considered nodes, provided that the working path used by each working link

is non-overlapping with other working paths used by other working links using the same wavelengths. In the case here considered, the second wavelength λ_y on the external ring 2 and the first wavelength λ_x on the internal ring 3 are not used under normal operative conditions, and are reserved for optical protection (i.e. are reserved for use in case of failure).

Each working link is under control of the two nodes at the end of the link itself. This means that, for a working link operating at working wavelengths $\lambda_{x,w}$, $\lambda_{y,w}$, the two nodes at the end of this link must provide the add/drop functions on working wavelengths $\lambda_{x,w}$ and $\lambda_{y,w}$ to/from the set of transmission wavelengths $\lambda_1, \dots, \lambda_N$. Moreover, all the required monitoring functions on the transmitted signals (e.g. optical power level, channel identifier, BER performance, etc.) have to be carried out at these terminating nodes. It has to be noted that the nodes not involved in communications on working wavelengths $\lambda_{x,w}$ and $\lambda_{y,w}$ do not provide any function on them, and these wavelengths are directly bypassed. Each node at the end of a working link using wavelengths $\lambda_{x,w}$ and $\lambda_{y,w}$ must also have the control on the protection wavelengths $\lambda_{x,p}$ and $\lambda_{y,p}$, being these wavelengths shared for protection among all the working links of the corresponding logical ring. The other nodes (i.e. the nodes external this logical ring) are not required to perform any operation on $\lambda_{x,p}$ and $\lambda_{y,p}$, and these wavelengths are simply bypassed in these nodes. As a general rule, the nodes not included in a logical ring (i.e. not terminating a generic working link on this logical ring) can be completely transparent to the wavelengths associated to the logical ring.

In the example of Figure 2, the working link between node 20c and node 20f operating on working wavelengths $\lambda_{x,w}$ and $\lambda_{y,w}$ is under control of these two nodes, and the working link between node 20d and 20e operating on the same wavelengths is under control of these two last nodes. Each of the nodes 20c, 20d, 20e and 20f has also the control on the protection wavelengths $\lambda_{x,p}$, $\lambda_{y,p}$ associated to the corresponding logical ring, in order to have access to the shared protection resource.

Nodes 20a and 20b cannot be part of the logical ring operating at working wavelengths. $\lambda_{x,w}$, $\lambda_{y,w}$ and may define termination nodes of working links at wavelengths different from $\lambda_{x,w}$, $\lambda_{y,w}$. Therefore, nodes 20a and 20b do not perform any action on working wavelengths $\lambda_{x,w}$, $\lambda_{y,w}$ and protection wavelengths $\lambda_{x,p}$, $\lambda_{y,p}$,

even if they may be required to provide optical amplification on the set of transmission wavelengths $\lambda_1, \dots, \lambda_N$. Furthermore, each node may be required to provide functions like regeneration or monitoring on the bypassed wavelengths, in order to allow a constant performance control of the set of transmission wavelengths
5 $\lambda_1, \lambda_2, \dots, \lambda_N$ over the entire ring network. Indeed, under failure conditions, these nodes have not to provide any reconfiguration action on the channels carried by the bypassed wavelengths.

With reference to Figure 3, the signal flow inside the generic node 20i, under normal operative conditions, is as follows.

10 In reception, the first and the second OADM 4, 5 drop the wavelengths of the logical rings to be managed. All the other wavelengths may be directly bypassed to the node output without any processing. In greater detail, the first OADM 4 drops from the set of transmission wavelengths $\lambda_1, \dots, \lambda_N$ on the external ring 2 both the working and protection wavelengths $\lambda_{x,w}$ and $\lambda_{y,p}$ (and possibly working and
15 protection wavelengths of other logical rings to be managed), while the second OADM 5 drops from the set of transmission wavelengths $\lambda_1, \dots, \lambda_N$ on the internal ring 3 both the working and protection wavelengths $\lambda_{y,w}$ and $\lambda_{x,p}$ (and possibly working and protection wavelengths of other logical rings to be managed). Wavelengths $\lambda_{x,w}$, $\lambda_{y,p}$, $\lambda_{y,w}$ and $\lambda_{x,p}$ are sent directly to the respective receiving
20 transponders $RxT_1(\lambda_x)$, $RxT_1(\lambda_y)$, $RxT_2(\lambda_y)$ and $RxT_2(\lambda_x)$, where, after conversion in electric format, information related to the link (link ~~signalling~~ **signaling**) is extracted and sent to the CPU 16 for processing. After processing, wavelengths $\lambda_{x,w}$, $\lambda_{y,p}$, $\lambda_{y,w}$ and $\lambda_{x,p}$ are newly converted in optical format.

The first working wavelength λ_w is then routed through switch unit 15 to the
25 first receiver Rx_1 and the second working wavelength $\lambda_{x,w}$ is routed through switch unit 15 to the second receiver Rx_2 . The first and the second protection wavelengths $\lambda_{x,p}$ and $\lambda_{y,p}$ are by-passed through switch unit 15 to the third transmitting transponder $TxT_2(\lambda_x)$ and, respectively, to the second transmitting transponder $TxT_1(\lambda_y)$, from where they are fed to the internal ring 3 and, respectively, to the external ring 2 by
30 the second OADM 5 and, respectively, the first OADM 4. ~~Signalling~~ **signaling** information carried by the protection wavelengths is left unchanged since no protection is required at the moment on the two working channels.

Signals generated by the first transmitter Tx_1 are routed through switch unit 15 to the first ~~transmitting~~ **transmitting** transponder $TxT_1(\lambda_x)$ for transmission on the first working wavelength $\lambda_{x,w}$, and signals generated by the second transmitter Tx_2 are routed through switch unit 15 to the fourth transmitting transponder $TxT_2(\lambda_x)$ for transmission on the second working wavelength $\lambda_{y,w}$. In the first and the fourth transmitting transponder $TxT_1(\lambda_x)$, $TxT_2(\lambda_x)$, appropriate information (link ~~signalling~~ **signaling**, channel identifier) generated by CPU 16 is added (for example by using bytes K1 and K2 as recommended in ITU-T standard) to signals on the first working wavelength $\lambda_{x,w}$ and, respectively, on the second working wavelength $\lambda_{y,w}$. These wavelengths are then sent respectively to the external and internal rings 2, 3 by OADM 4, 5.

Identical operations are performed in each receiving/transmitting module included in node 20i, for corresponding pairs of wavelengths that have to be managed by this node.

When a failure occurs, reconfiguration takes place in all those, and only those, logical rings including at least a working link whose transmission is affected by the failure. It is intended that the failure can be everything affecting the transmission between two nodes, therefore not only a fiber cut but also a failure in a node device such as a OADM or a transponder. Reconfiguration in a logical ring is performed independently from reconfiguration in the other logical rings. In particular, for each working link affected by the failure, reconfiguration takes place only at the pair of nodes terminating the link, while the nodes interposed between these terminating nodes do not perform any action to restore the failed link.

As a consequence of a failure on the generic working link operating at the working wavelengths $\lambda_{x,w}$, $\lambda_{y,w}$, the two nodes terminating the working link detect the failure condition (in the way hereinbelow described) and run the reconfiguration process by switching the transmission on the respective protection arc path using the protection wavelengths $\lambda_{x,p}$, $\lambda_{y,p}$. In practice, signals previously transmitted at the first working wavelength $\lambda_{x,w}$ on the external ring 2 are switched at the first protection wavelength $\lambda_{x,p}$ on the internal ring 3, while signals previously

transmitted at the second working wavelength $\lambda_{y,w}$ on the internal ring 3 are switched, at the second protection wavelength $\lambda_{y,p}$ on the external ring 2.

The working link between the two nodes is consequently re-routed on the respective protection path by using the protection wavelengths $\lambda_{x,p}$, $\lambda_{y,p}$, if
5 necessary through nodes which are terminating other working links on the same logical ring. These last nodes do not have to perform any action as a consequence of the reconfiguration process performed by the nodes terminating the working link affected by the failure, but must be aware of the presence of a signal carried by the protection wavelengths in order to know that the protection resource has been taken
10 by another working link of the same logical ring. Therefore, as a consequence of the protection operations performed on the failed working link, all the other working links of the same logical ring become unprotected. This situation persist until the failure has been repaired and the transmission previously switched on the protection path has been restored on the original working link. Moreover, nodes which
15 terminate working links sharing the same protection resource of the failed one (i.e. the working links of the same logical ring) must have the protection mechanism inhibited until normal conditions are restored.

Figure 9 depicts a situation in which a failure occurs in the ring network of Figure 2 between nodes 20a and 20b. According to the above, nodes 20a and 20b do
20 not perform any action in response to the failure because, in the particular condition disclosed, they are not terminating nodes of a working link affected by the failure.

The hereinbelow described sequence of operations for the failure detection and ~~signalling~~ **signaling** performed by nodes 20c and 20f is to be considered only as an example. Different sequence of operations may alternatively be used, without
25 depart from the scope of the present invention, all leading to a transitory condition at the end of which nodes 20c and 20f are both reconfigured.

Supposing that the failure affects only the transmission from node 20f to node 20c (along the internal ring 3), while the opposite transmission (along the external ring 2) is still operative, node 20c detects the absence of signals or a signal quality
30 degradation (corresponding, for example, to a BER over a predetermined threshold) at the second working wavelength $\lambda_{y,w}$ on the fourth receiving transponder

RxT₂(λ_y) and, consequently, its CPU 16 operates a reconfiguration of its switch unit 15 (as hereinbelow described with reference to Figure 10) in order to switch the transmission (in the manner described below) on the protection path. Before reconfiguration takes place, node 20c sends node 20f a failure message preferably
5 along both the external ring 2 (in the counter-clockwise direction) and the internal ring 3 (in the clockwise direction) and preferably by using the protection wavelengths $\lambda_{y,p}$ and $\lambda_{y,p}$ to inform node 20f of the new situation.

In the preferred case of the bidirectional message transmission, node 20f receives the message from both the external ring 2 and the internal ring 3 (for
10 example at the protection wavelengths $\lambda_{x,p}$ and $\lambda_{x,p}$) and reacts by performing the reconfiguration of its switch unit 15 (as shown in Figure 13), consequently switching the transmission on the respective protection path.

On the other hand, if the failure affects only the transmission from node 20c to node 20f (along the external ring 2), a similar sequence of operations is performed
15 starting from node 20f.

Alternatively, if both the transmission directions are affected by the failure, the first one between nodes 20c and 20f becoming aware of the absence of signals or of a signal quality degradation sends the other node the failure message (preferably along both the external ring 2 and the internal ring 3 and preferably by using the
20 protection wavelengths $\lambda_{y,p}$ and $\lambda_{y,p}$) and subsequently operates a reconfiguration of its switch unit 15. The other node realizes the presence of a failure in the considered link either as a consequence of the detection of the absence of signals or of a signal quality degradation, or as a consequence of the reception of the failure message from the first node (and only from one direction, in the preferred case of the
25 bidirectional message transmission) and, in its turn, sends a failure message to the first node and operates a reconfiguration of its switch unit 15.

At the end of the above transitory condition, signals transmitted between nodes 20c and 20f are carried on the respective protection path. Nodes 20d and 20e, which, in the example of Figure 2, are the termination nodes of another working link
30 in the same logical ring, are informed of the new situation by checking the status of

the channel carried by the protection wavelengths bypassed (i.e. by reading the failure message), and they consequently inhibit their protection mechanism.

When the failure has been repaired, the normal condition can be restored on each affected logical ring by resetting the switching layouts at the terminating nodes of the failed working links so as to re-route such links on their original working path. On the generic logical ring, all the link terminating nodes not previously affected by the failure are informed of the release of the shared protection capacity by checking the status of the channel carried by the protection wavelengths (which are now unused). As a consequence, these link terminating nodes re-enable their protection mechanism.

Figure 10 depicts the situation in which a failure occurs on a working link defined by the generic node 20i (together with a further node not shown), in particular a failure on the left-hand side of node 20i. Node 20i is informed of the failure condition by detecting, at the fourth receiving transponder $RxT_2(\lambda_y)$, the absence of signals, or a signal quality degradation (like a BER over a predetermined threshold), or the reception of a failure message (as previously described). CPU 16 consequently generates an appropriate failure message to be sent to the other terminating node of the working link, preferably along both the external ring 2 and the internal ring 3. CPU 16 preferably feeds this failure message to the second transmitting transponder $TxT_1(\lambda_y)$ for transmission at the second protection wavelength $\lambda_{y,p}$ and to the third transmitting transponder $TxT_2(\lambda_w)$ for transmission at the first protection wavelengths $\lambda_{x,p}$. CPU 16 subsequently operates the reconfiguration of switch unit 15, by reconfiguring switches 22 and 23 from the bypass status to the switched status in order to bypass the failed working path and re-route the transmission towards the other node of the failed working link on the respective protection path.

In the new node configuration, the first transmitter Tx_1 is connected to the third transmitting transponder $TxT_2(\lambda_x)$ and the corresponding signals are then sent on the internal ring 3 in clockwise direction, while the first receiver Rx_1 is connected to the second receiving transponder $RxT_1(\lambda_y)$ and the signals are then received from the external ring 2 in counter-clockwise direction. If the considered node includes a

switch unit 15' (1x2 and 2x1 switches) or a switch unit 15" (integrated optics) in place of switch unit 15 (2x2 switches), the reconfigured status of the corresponding switch unit is as shown in Figure 11 and, respectively, in Figure 12.

The node at the other end of the affected link performs the same operations, after receiving a failure message from the other node, or after detecting the absence of signals or a signal quality degradation at its first receiving transponder $RxT_1(\lambda_x)$. The working link between the two nodes is consequently re-routed on the protection path associated to the working link. Both the reconfigured nodes have also to update the ~~signalling~~ signaling information (generated by the respective CPUs and added to the transmitted signals in the respective transmitting transponders $TxTs$) carried by the protection wavelengths $\lambda_{x,p}$, $\lambda_{y,p}$ in order to inform all the other nodes on the same logical ring that the shared resource is at present used by the two considered nodes.

When the failure has been repaired, both the nodes at the end of the affected link can be restored to the normal operative condition of Figure 3, thus releasing the shared protection resource.

In nodes including more than one receiving/transmitting module 6, the described protection mechanism operates independently for each module 6.

Figures 13-15 depicts the situation in which a failure occurs on the right-hand side of the generic node 20i. The reconfiguration process is very similar to the one referred to the left-hand side failure and is not here described.

It is intended that, without depart from the scope of the present invention, the architecture of the nodes may be arranged so that, in the absence of failures, protection wavelengths $\lambda_{x,p}$ on the internal ring 3 and $\lambda_{y,p}$ on the external ring 2 may be used to transport low-priority in the same direction as the other wavelengths on the same ring.

Additional network functionality may be obtained if the ring network includes switch units as depicted in Figure 16. In detail, Figure 16 shows a switch unit 215 including:

- a first, a second, a third, a fourth, a fifth and a sixth 3-dB splitter 221-226 having the respective inputs coupled to the first transmitter Tx_1 (via the first

signal input IN_1), the third receiving transponder $RxT_2(\lambda_x)$, the first receiving transponder $RxT_1(\lambda_x)$, the fourth receiving transponder $RxT_2(\lambda_y)$, the second receiving transponder $RxT_1(\lambda_y)$ and the second transmitter Tx_2 (via the second signal input IN_2), respectively;

5 - a first, a second, a third, a fourth, a fifth and a sixth switch 231-236 of the 2x1 type, wherein:

- 10 ▪ the first switch 231 has a first input coupled to a second output of the first splitter 221, a second input coupled to a first output of the second splitter 222 and an output coupled to the third transmitting transponder $TxT_2(\lambda_x)$;
- the second switch 232 has a first input coupled to a second output of the second splitter 222, a second input coupled to a first output of the third splitter 223 and an output coupled to the second receiver Rx_2 (via the second signal output OUT_2);
- 15 ▪ the third switch 233 has a first input coupled to a first output of the first splitter 221, a second input coupled to a second output of the third splitter 223 and an output coupled to the first transmitting transponder $TxT_1(\lambda_x)$;
- the fourth switch 234 has a first input coupled to a second output of the fourth splitter 224, a second input coupled to a first output of the fifth splitter 225 and an output coupled to the first receiver Rx_1 (via the first signal output OUT_1);
- 20 ▪ the fifth switch 235 has a first input coupled to a second output of the fifth splitter 225, a second input coupled to a first output of the sixth splitter 226 and an output coupled to the second transmitting transponder $TxT_1(\lambda_y)$;
- 25 ▪ the sixth switch 236 has a first input coupled to a first output of the fourth splitter 224, a second input coupled to a second output of the sixth splitter 226 and an output coupled to the fourth transmitting transponder $TxT_2(\lambda_y)$.
- 30

Switches 231-236 may be optomechanical switches, for example of the type produced by JDS FITELE, INC., 570 Heston Drive, Nepean, Ontario (CA) or of the type produced by E-TEK DYNAMICS, INC., 1885 Lundy Ave., San Jose, CA (USA). Splitters 221-226 may be of a known type, for example those produced by E-TEK DYNAMICS, INC., 1885 Lundy Ave., San Jose, CA (USA). Alternatively, switch unit 215 may be made in integrated optics (preferably in the lithium niobate technology), and its components (switches 231-236 and splitters 221-226) may be realized on a single chip.

Figures 17 and 18 are schematic representations of signal routing (heavy lines) in the switch unit 215 under normal operative conditions and, respectively, in case of failure on the left-hand side of the considered node. Under normal operative conditions, signals routing among transponders, transmitters and receivers within the nodes is the same as previously described. As a reaction to failure (detected or signaled) on the left-hand side of the node, the first switch 231 is switched so as to couple the third transmitting transponder $TxT_2(\lambda_x)$ to the first transmitter Tx_1 (via the first signal input IN_1 and the first splitter 221) and the fourth switch 234 is switched so as to couple the first receiver Rx_1 (via the first signal output OUT_1) to the second receiving transponder $RxT_1(\lambda_y)$ (via the fifth splitter 225). The first transmitter Tx_1 is then allowed to transmit signals in both the working channel of the external ring 2 (as before the failure) and the protection channel of the internal ring 3 (in the opposite direction); at the same time, signals received by the second receiving transponder $RxT_1(\lambda_y)$ from the protection channel of the external ring 2 are fed (via the fifth splitter 225, the fourth switch 234 and the fifth switch 235) to both the second transmitting transponder $TxT_1(\lambda_y)$ (as before the failure) and the first receiver Rx_1 .

The described switching architecture allows the following additional functionality: continuous monitoring of working and protection lines, flexible channel add/drop or node by-pass, multicasting/broadcasting of working and protection channels with "drop & continue" and multi-ring interconnection with "drop & continue".

1) Continuous monitoring of working and protection lines: when a failure occurs, signal transmission in the direction of the failure does not stop; this allows a continuous monitoring of the ~~failed~~ **failure**, channels and an immediate re-establishment of the ~~failed~~ **failed** communication when the fault is repaired.

5 2) Flexible Channel Add/Drop: This solution allows flexible optical channel add/drop at node site. By flexible add/drop of an optical channel (i.e. a wavelength) it is intended the ability to configure the network in order to add and/or drop an optical channel in a specific node or let it pass through towards a different destination, without interfering with the protection signal routing. This process can be controlled
10 locally or remotely.

3) Multicasting/broadcasting of working and protection channels: by choosing the appropriate switching condition of switch unit 215, it is possible to perform, under both normal and failure conditions, a multicasting/broadcasting transmission. Broadcasting is the process of sending a signal or message from one
15 node (or station) of the network to all other nodes of the network, while multicasting is the process of sending a signal or message from one node of the network to a selected subset of all other nodes of the network. Switch unit 215 may be configured so as to allow dropping of an optical channel at the node site and at the same time letting it pass through the node. In this way it is possible to send the same signal
20 from one transmission point to multiple receiver points (i.e. point-to-multi-point connection). For example, multicasting/broadcasting of the working channel ($\lambda_{x,w}$) transmitted onto the external ring 2 is performed, as illustrated in Figure 19, by operating the second and the third switch 232, 233 so as to couple the first receiving transponder $RxT_1(\lambda_x)$ to both the second receiver Rx_2 (via the second signal output
25 OUT₂) and the first transmitting transponder $TxT_1(\lambda_x)$ (via the third splitter 223); accordingly, signals on working channel $\lambda_{x,w}$ are both received into the considered node and re-transmitted onto the external ring 2. During broadcast of working channel $\lambda_{x,w}$, the first transmitter Tx_1 is operatively disconnected from the first transmitting transponder $TxT_1(\lambda_x)$. Similarly, broadcasting of the working channel
30 $\lambda_{y,w}$ of the internal ring 3 is performed by operating the fourth and the sixth switch

234, 236 so as to couple (via the fourth splitter 224) the fourth receiving transponder $RxT_2(\lambda_y)$ to both the first receiver Rx_1 (via the first signal input IN_1) and the fourth transmitting transponder $TxT_2(\lambda_y)$; therefore, signals on working channel $\lambda_{y,w}$ are both received into the considered node and re-transmitted onto the internal ring 3.

5 During broadcast of working channel $\lambda_{y,w}$, the second transmitter Tx_2 is operatively disconnected from the fourth transmitting transponder $TxT_2(\lambda_y)$. In the same way, as illustrated in Figure 20, it is possible to perform the broadcasting of the protection channel $\lambda_{x,p}$ by operating the first and the second switch 231, 232 so that the third receiving transponder $RxT_2(\lambda_x)$ is coupled to both the third transmitting transponder

10 $TxT_2(\lambda_x)$ and the second receiver Rx_2 and the broadcasting of the protection channels $\lambda_{y,p}$ by operating the fourth and the fifth switch 234, 235 so that the second receiving transponder $RxT_1(\lambda_y)$ is coupled to both the second transmitting transponder $TxT_1(\lambda_y)$ and the first receiver Rx_1 . During broadcast of protection channel $\lambda_{x,p}$, the first transmitter Tx_1 can be operatively connected to the first

15 transmitting transponder $TxT_1(\lambda_x)$ and during broadcast of protection channel $\lambda_{y,p}$, the second transmitter Tx_2 can be operatively connected to the fourth transmitting transponder $TxT_2(\lambda_y)$. It is possible to perform the simultaneous broadcast of channels $\lambda_{x,w}$ and $\lambda_{y,w}$, of channels $\lambda_{x,w}$ and $\lambda_{y,p}$, of channels $\lambda_{y,w}$ and $\lambda_{x,p}$ and of channels $\lambda_{x,p}$ and $\lambda_{y,p}$.

20 4) Multi-ring interconnection: two or more different ring networks can exchange signals in the way hereinbelow described. Figure 21 shows two ring networks, identified as Network 1 and Network 2, each having a plurality of nodes for client communication and a pair of nodes for signal exchange with the other ring network. In particular, Network 1 includes three nodes A, B, C for client communication, and a primary and a secondary node D, E ("gateways") for signal

25 exchange with Network 2. Network 2 includes three nodes A', B', C' for client communication, and a primary and a secondary node D', E' ("gateways") for signal exchange with nodes D and E, respectively. Nodes D, E, D' and E' differ from the

other nodes in that in place of transmitters Tx₁, Tx₂ and receivers Rx₁, Rx₂ there are optical connections with the corresponding nodes of the other ring network. In detail:

- splitter 221 of node D (D') is optically connected to switch 232 of node D' (D);
- 5 - splitter 226 of node D (D') is optically connected to switch 234 of node D' (D).

Analogous connections are present between nodes E and E'.

- In the considered example, a signal S₁ at λ_x is transmitted from node B to node C' and a signal S₂ at wavelength λ_y is transmitted from node C' to node B.
- 10 Under normal operative conditions, signal S₁ is inserted into the first ring network (Network 1) by node B, passes through node C and is received by node D, where it is split into a first and a second fraction (50% of power) which are sent towards nodes E and D'. This functionality is called "drop and continue". Node D' selects signal S₁ coming from node D or node E' and transmits it to node C', where it is extracted. In a
- 15 similar way, signal S₂ is transmitted from node C' to node B via nodes D' and D.

In more detail, signal routing within the different nodes during normal operative conditions are the following:

- Node B

- Signal S₁ is inserted at the first input IN₁ and transmitted via the first transmitting transponder TxT₁(λ_x).
- 20 Signal S₂ is received from the fourth receiving transponder RxT₂(λ_y) and extracted at the first output OUT₁.

- Node C

- Signal S₁ is received via the first receiving transponder RxT₁(λ_x) and continues via the first transmitting transponder TxT₁(λ_x).
- 25 Signal S₂ is received via the fourth receiving transponder RxT₂(λ_y) and continues via the [[first]] **fourth** transmitting transponder TxT₂(λ_y).

- Node D

- Signal S₁ is received via the first receiving transponder RxT₁(λ_x) and it is both
- 30 dropped at the second output OUT₂ and continued via the first transmitting transponder TxT₁(λ_x).

Signal S_2 is received via both the second input IN_2 and the fourth receiving transponder $RxT_2(\lambda_y)$; the sixth switch 236 is operated so as to connect the fourth transmitting transponder $TxT_2(\lambda_y)$ to the second input IN_2 under normal operative conditions and to the fourth receiving transponder $RxT_2(\lambda_y)$ when nodes D and D' cannot communicate.

- Node E

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and it is dropped at the second output OUT_2 .

Signal S_2 is received via the second input IN_2 and transmitted via the fourth receiving transmitting transponder $TxT_2(\lambda_y)$.

- Node D'

Signal S_1 is received via both the first input IN_1 and the first receiving transponder $RxT_1(\lambda_x)$; the third switch 233 is operated so as to connect the first transmitting transponder $TxT_1(\lambda_x)$ to the first input IN_1 under normal operative conditions and to the first receiving transponder $RxT_1(\lambda_x)$ when a failure avoids correct transmission between nodes D and D'.

Signal S_2 is received from the fourth receiving transponder $RxT_2(\lambda_y)$ and it is both dropped at the first output OUT_1 and continued via the fourth transmitting transponder $TxT_2(\lambda_y)$.

- Node E'

Signal S_1 is received via the first input IN_1 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and it is dropped at the first output OUT_1 .

- Node C'

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and extracted at the second output OUT_2 .

Signal S_2 is inserted at the second input IN_2 and transmitted via the fourth receiving transponder $TxT_2(\lambda_y)$.

The bi-directional connection between nodes B and C' is protected against independent failures in Network 1 and Network 2 and also in case of a gateway failure (e.g. in case of failure of nodes D, D', E or E'). When a failure occurs on one

of the two rings (or on both), communication is switched onto the protection channels and signals S_1 and S_2 are still transferred between the two rings by the D-D' (primary nodes) connection. Figure 22 illustrates a possible failure condition, in which the communication is interrupted between nodes B and C. In this case, signals

5 S_1 and S_2 are conveyed along the complementary path through node A. In brief, signal S_1 is transmitted by node B onto the protection channel $\lambda_{x,p}$ of the internal ring 3, passes through nodes A and E and is received by node D, where the second splitter 222 feeds a fraction of it to the second switch 232, and this last operates so as to

10 transmit signal S_1 at $\lambda_{x,p}$ towards node D'. Node D' receives signal S_1 at the input of its first splitter 221 and sends it, via its third switch 233 and its first transmitting transponder $TxT_1(\lambda_x)$, to node C', where it is extracted in the same way as above. Analogously, signal S_2 is transmitted to node B by exploiting the protection channel $\lambda_{y,p}$ of the external ring.

In more detail, the signal routing within the different nodes during a failure

15 condition as the one illustrated in Figure 22, is the following:

- Node B

Signal S_1 is inserted at the first input IN_1 and transmitted via the third transmitting transponder $TxT_2(\lambda_x)$.

Signal S_2 is received via the second receiving transponder $RxT_1(\lambda_y)$ and

20 extracted at the first output OUT_1 .

- Node A

Signal S_1 is received via the third receiving transponder $RxT_2(\lambda_x)$ and it is transmitted via the third transmitting transponder $TxT_2(\lambda_x)$.

Signal S_2 is received via the second receiving transponder $RxT_1(\lambda_y)$ and

25 transmitted via the second transmitting transponder $TxT_1(\lambda_y)$.

- Node E

Signal S_1 is received via the third receiving transponder $RxT_2(\lambda_x)$ and it is both dropped at the second output OUT_2 and transmitted via the third transmitting transponder $TxT_2(\lambda_x)$.

Signal S_2 is received via both the second input IN_2 and the second transmitting transponder $RxT_1(\lambda_y)$: the fifth switch 235 is operated so as to

30

connect the second transmitting transponder $TxT_1(\lambda_y)$ to either the second input IN_2 or the second transmitting transponder $RxT_1(\lambda_y)$.

- Node D'

5 Signal S_1 is received via both the first input IN_1 and the first receiving transponder $RxT_1(\lambda_x)$: the third switch 233 is operated so as to connect the first transmitting transponder $TxT_1(\lambda_x)$ to either the first input IN_1 and the first receiving transponder $RxT_1(\lambda_x)$.

10 Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and it is both dropped at the first output OUT_1 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

- Node E'

Signal S_1 is received from the first input IN_1 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

15 Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and dropped at the first output OUT_1 .

- Node C'

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and extracted at the second output OUT_2 .

20 Signal S_2 is inserted at the second input IN_2 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

25 In case of failure of gateway node D, communication between nodes B and C' and, in general, between Network 1 and Network 2, can be guaranteed by the optical connection between the secondary nodes E and E'. In fact, when the said failure is detected, the switch units 215 of nodes E and E' are operated so as to perform the required routing operations (i.e. the same routing operations previously performed by nodes D and D'). Networks signal exchange via nodes E and E' continues until communication between nodes D and D' is restored.

In detail, signal routing when a failure occurs in node D is as hereinbelow described with reference to Figure 23:

30 • Node B

Signal S_1 is inserted at the first input IN_1 and transmitted via the third transmitting transponder $TxT_2(\lambda_x)$.

Signal S_2 is received via the second transmitting transponder $RxT_1(\lambda_y)$ and extracted at the first output OUT_1 .

- Node A

Signal S_1 is received via the third receiving transponder $RxT_2(\lambda_x)$ and it is transmitted via the third transmitting transponder $TxT_2(\lambda_x)$.

Signal S_2 is received via the second receiving transponder $RxT_1(\lambda_y)$ and transmitted via the second transmitting transponder $TxT_1(\lambda_y)$.

- Node D

Not used (because of failure)

- Node E

Signal S_1 is received via the third receiving transponder $RxT_2(\lambda_x)$ and dropped at the second output OUT_2 .

Signal S_2 is received via the second input IN_2 only; the fifth switch 235 is operated so as to connect the second transmitting transponder $TxT_1(\lambda_y)$ to the second input IN_2 .

- Node D'

Signal S_1 is received via the first transmitting transponder $RxT_1(\lambda_x)$ only; the third switch 233 is operated so as connect the first transmitting transponder $TxT_1(\lambda_x)$ to the first transmitting transponder $RxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

- Node E'

Signal S_1 is received via the first input IN_1 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and it is dropped at the first output OUT_1 .

- Node C'

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and extracted at the second output OUT_2 .

Signal S_2 is inserted at the second input IN_2 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

Communication between nodes B and C' and, in general, between Network 1 and Network 2, can be guaranteed by the optical connection between the secondary nodes E and E' even in case of failure on the D-D' optical connection, as illustrated in Figure 24. In fact, when such a failure is detected, switch units 215 of nodes E and E' are operated so as to perform the required routing operations. Rings signal exchange via nodes E and E' continues until communication between nodes D and D' is restored.

In detail, signal routing in the different nodes during a connection failure between nodes D and D' is as follows:

10 • Node B

Signal S_1 is inserted at the first input IN_1 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and extracted at the first output OUT_1 .

15 • Node C

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and continues via the first transmitting transponder $TxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and continues via the first transmitting transponder $TxT_2(\lambda_y)$.

20 • Node D

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and it is both dropped at the second output OUT_2 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

25 Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ only: the first switch 231 is operated so as to connect the fourth transmitting transponder $TxT_2(\lambda_y)$ to the fourth ~~receiving~~ **receiving** transponder $RxT_2(\lambda_y)$.

• Node E

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and dropped at the second output OUT_2 .

30 Signal S_2 is received via the second input IN_2 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

- Node D'

Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ only: the third switch 233 is operated so as to connect the first transmitting transponder $TxT_1(\lambda_x)$ to the first receiving transponder $RxT_1(\lambda_x)$.

5 Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and it is both dropped at the first output OUT_1 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

- Node E'

10 Signal S_1 is received via the first input IN_1 and transmitted via the first transmitting transponder $TxT_1(\lambda_x)$.

Signal S_2 is received via the fourth receiving transponder $RxT_2(\lambda_y)$ and dropped at the first output OUT_1 .

- Node C'

15 Signal S_1 is received via the first receiving transponder $RxT_1(\lambda_x)$ and extracted at the second output OUT_2 .

Signal S_2 is inserted at the second input IN_2 and transmitted via the fourth transmitting transponder $TxT_2(\lambda_y)$.

WHAT IS CLAIMED IS:

[[1]] **1.** (Amended) ~~An Autoprotected~~ **autoprotected** optical communication ring network, ~~including~~ **comprising:**

5 a first and a second optical carrier ~~[(2, 3)]~~ having opposite transmission directions; and

a plurality of optically reconfigurable nodes ~~(20a-20f)~~ optically connected along the first and ~~[[the]]~~ second optical ~~carrier~~ **carriers** ~~[(2, 3)]~~ and adapted to communicate in pairs by ~~means of~~ respective links susceptible ~~[[of]]~~ **to** failure, the ring network having a nominal operative condition in which the nodes of each

10 ~~[[pair]]~~ **of the pairs** are optically configured so as to exchange optical signals on a respective working arc path at a respective first wavelength (λ_x) on the first carrier ~~[(2)]~~ and at a respective second wavelength (λ_y) different from said first wavelength (λ_x) on the second carrier ~~[(3)]~~, said respective working path having a complementary arc path defining a ~~respective~~ protection arc path in which the first

15 wavelength (λ_x) on the first carrier ~~[(2)]~~ and the second wavelength (λ_y) on the second carrier ~~[(3)]~~ can be used for further links and the first wavelength (λ_x) on the second carrier ~~[(3)]~~ and the second wavelength (λ_y) on the first carrier ~~[(2)]~~ are reserved for protection, ~~characterized in~~ **such** that the ring network has a failure operative condition in which the nodes terminating a ~~failed~~ **failed** link are optically

20 reconfigured so as to exchange optical signals on the ~~respective~~ protection arc path at the respective second wavelength (λ_y) on the first carrier ~~[(2)]~~ and at the respective first wavelength (λ_x) on the second carrier ~~[(3)]~~, **wherein the reconfiguration of one or more of the nodes reflects reconfiguration at a channel level associated with the ring network.**

[[2))] 2. (Amended) The [[Ring]] ring network according to claim of Claim 1, wherein each of said plurality of reconfigurable nodes (20a-20f) is adapted configured to manage a predetermined subset of wavelengths within a set of transmission wavelengths, $(\lambda_1, \lambda_2, \dots, \lambda_N)$ and wherein each of the nodes includes a first and a second optical add/drop multiplexer [[(4, 5)]] that may be serially connected to said first and, ~~respectively,~~ second carrier carriers [[(2, 3)]] respectively in order to feed/extract communicate said subset of wavelengths to[[/from]] said first and, ~~respectively,~~ second carrier carriers (2, 3), and to pass-through the remaining wavelengths of the set of transmission wavelengths $(\lambda_1, \lambda_2, \dots, \lambda_N)$.

[[3))] 3. (Amended) The [[Ring]] ring network according to claim of Claim 1 [[or 2]], wherein said plurality of reconfigurable nodes (20a-20f) includes at least a signal input, (IN_1, IN_2) , at least a signal output, (OUT_1, OUT_2) and a reconfigurable optical switch unit (15; 15'; 15"; 115'; 115"; 215) ~~selectively coupling~~ operable to couple said at least an signal input (IN_1, IN_2) and said at least a signal output (OUT_1, OUT_2) to said first and second carriers [[(2, 3)]] respectively.

[[4))] 4. (Amended) The [[Ring]] ring network according to claim of Claim 3, wherein said at least a signal input (IN_1, IN_2) is optically coupled to a ~~respective~~ an optical transmitter [[(TX₁)]] and said at least a signal output (OUT_1, OUT_2) is optically coupled to a ~~respective~~ an optical receiver [[(Rx₁)]].

[[5))] 5. (Amended) The [[Ring]] ring network according to claim of Claim 3 [[or 4]], wherein each of said plurality of reconfigurable nodes (20a-20f) includes information insertion devices (TxTs) ~~selectively optically connectable~~ coupled to said at least a signal input (IN_1, IN_2) and adapted to [[insert]] position signalling signaling information into one or more [[the]] optical signals and ~~information extraction devices (RxTs) selectively optically connectable to said at least a signal output (OUT_1, OUT_2) and adapted to extract signalling information from the optical signals.~~

5 ~~[[6]]~~ **6. (Amended) The ~~[[Ring]]~~ ring network according to claim of Claim**
5, wherein said information insertion devices (TxTs) ~~and said information extraction~~
devices (RxTs) include optical transponders operable to optically ~~coupling~~ couple
said optical switch unit ~~(15; 15'; 15"; 115'; 115"; 215)~~ to said first and second ~~carrier~~
carriers ~~(2, 3) and adapted to change the signals wavelengths.~~

7) **7. (Amended) The ~~[[Ring]]~~ ring network according to claim of Claim**
3, wherein at least one of said reconfigurable nodes ~~(20a-20f)~~ includes at least a first
signal ~~spitter~~ splitter ~~(222-225)~~ adapted to receive a signal from either a selected
10 one of the first ~~[[or]]~~ and the second ~~carrier~~ carriers ~~[[(2, 3)]]~~ and to split said signal
into a first and a second fraction ~~which are sent towards~~ to be communicated toward
a ~~respective~~ signal output ~~(OUT₁, OUT₂) and towards the same carrier (2, 3),~~
respectively.

15 ~~[[8]]~~ **8. (Amended) The ~~[[Ring]]~~ ring network according to claim of Claim**
~~[[3]]~~ **7**, wherein at least a selected one or more of said reconfigurable nodes includes
at least a second signal ~~spitter~~ splitter ~~(2:21, 226)~~ optically coupled to a ~~respective~~
signal input ~~(IN₁, IN₂)~~ and adapted to ~~[[spit]]~~ split a signal coming from the
~~respective~~ signal input ~~(IN₁, IN₂)~~ into a first and a second fraction ~~which are sent~~
20 ~~towards~~ to be communicated toward the first ~~carrier~~ (2) and ~~[[the]]~~ second ~~carrier~~
carriers ~~[[(3),]]~~ respectively.

9) **9. (Amended) The ~~[[Ring]]~~ ring network according to claim of Claim**
3, wherein said optical switch unit ~~[[(215)]]~~ includes at least a first switch ~~(231, 233,~~
25 ~~235, 236)~~ having a first input that is optically coupled to a ~~respective~~ signal input
~~(IN₁, IN₂)~~, a second input coupled to either the first or the second carrier (2, 3) and an
output coupled to the same carrier (2, 3).

10) **10. (Amended) The** ~~[[Ring]]~~ **ring** network ~~according to claim of Claim~~
[[8]] **9**, wherein said optical switch unit ~~[[215]]~~ includes ~~at least~~ a second switch
(232, 234) having a first input **that is** coupled to the first carrier ~~[[2]]~~ and a second
input **that is** coupled the second carrier ~~[[3]]~~, and **wherein** an output **of the second**
5 **switch is** optically coupled to a ~~respective~~ signal output ~~(OUT₁, OUT₂)~~.

11) **(Canceled)** Optical transmission system, including a first and a second ring
network according to claim 3, wherein a first reconfigurable node (D) of the first ring
network has a signal input (IN₁, IN₂) which is optically coupled to a signal output
10 (OUT₁, OUT₂) of a second reconfigurable node (D') of the second ring network.

12) **(Canceled)** Optical transmission system according to claim 11, wherein the
second reconfigurable node (D') has a signal input (IN₁, IN₂) which is optically
coupled to a signal output (OUT₁, OUT₂) of the first reconfigurable node (D).
15

13) **(Canceled)** Optical transmission system according to claim 11, wherein a
third reconfigurable node (E) of the first ring network has a signal input (IN₁, IN₂)
which is optically coupled to a signal output (OUT₁, OUT₂) of a fourth
reconfigurable node (E') of the second ring network, and the fourth reconfigurable
20 node (E') has a signal input (IN₁, IN₂) which is optically coupled to a signal output
(OUT₁, OUT₂) of the third reconfigurable node (E).

14) **14. (Amended) A method** ~~Method~~ to autoprotect an optical ring network, said ring network including a first and a second optical carrier having opposite transmission directions and a plurality of nodes optically connected along the first and the second optical ~~carrier~~ **carriers** and adapted to communicate in pairs
5 in order to define bidirectional links, each ~~[[pair]]~~ **of the pairs** including a first and a second link termination node adapted to mutually communicate at respective first and second wavelengths, the method ~~including~~ **comprising**:

exchanging signals between the first and the second link termination ~~[[node]]~~
nodes ~~of each pair~~ on a ~~respective~~ working arc path of said ring network by using the
10 ~~respective~~ first wavelength on the first carrier and the ~~respective~~ second wavelength on the second carrier~~[[,]]~~, said ~~respective~~ working path having a complementary arc path defining a ~~respective~~ protection arc path in which the first wavelength on the first carrier and the second wavelength on the second carrier can be used for further links, **wherein** ~~[[and]]~~ the first wavelength on the second carrier and the second
15 wavelength on the first carrier are reserved for protection;

checking if a failure is present in the ring network producing ~~at least a~~
~~failed~~ **failed** link; and

optically reconfiguring, in the presence of ~~[[a]]~~ **the** failure, the link terminating nodes of said ~~at least a failed~~ **failed** link so that ~~they exchange~~ signals
20 **may be exchanged** on the ~~respective~~ protection arc path by using the ~~respective~~ first wavelength on the second carrier and the ~~respective~~ first wavelength on the second carrier, **wherein the reconfiguration of one or more of the nodes reflects reconfiguration at a channel level associated with the ring network.**

25 15) **15. (Amended) The method** ~~Method according to claim~~ **of Claim** 14, wherein each node of said plurality of nodes is adapted to manage a predetermined subset of wavelengths within a set of transmission wavelengths carried by the first and the second ~~carrier~~ **carriers**, said step of exchanging including optically separating, at each node of said plurality of nodes, each wavelength of the ~~respective~~
30 subset of wavelengths from ~~[[the]]~~ **a** set of transmission wavelengths.

[[16]] **16. (Amended) The method Method according to claim of Claim 14, including the steps of further comprising:**

inserting a signal into one of said nodes[.];

splitting said signal into a first and a second fraction; and

5 sending said first fraction ~~towards~~ **toward** the first carrier and the second
[[power]] fraction ~~towards~~ **toward** the second carrier.

[[17]] **17. (Amended) The method Method according to claim of Claim 14, including the steps of further comprising:**

10 receiving a signal in one of said nodes from either the first or the second
carrier[.];

splitting said signal into a first and a second fraction; **and**

sending the first **fraction** ~~towards~~ **toward** the same carrier and the second
fraction towards a signal output of said node.

15

18) **(Canceled)** Method according to claim 14, wherein the step of checking
includes verifying, in each node of said plurality of nodes and for each wavelength of
the respective set of wavelengths, if signals are received.

20 19) **(Canceled)** Method according to claim 14, wherein said step of checking
includes verifying, in each node of said plurality of nodes and for each wavelength of
the respective set of wavelengths, if signals are received degraded.

25 20) **(Canceled)** Method according to claim 14, wherein said step of checking
includes verifying, in each node of said plurality of nodes and for each wavelength of
the respective set of wavelengths, if signals include a failure message.

21) **21. (Amended) The method** ~~Method according to claim~~ **of Claim 14,**
further including **comprising:**

transmitting a failure message from [[a]] ~~the~~ first link termination node of a
pair to [[a]] ~~the~~ second link termination node of the same pair if a signal transmitted
5 from the second link termination node to the first link termination node is not
received[[,]] or is received degraded, by the first link termination node.

[[22))] **22. (Amended) The method** ~~Method according to claim~~ **of Claim 14,**
wherein said step of **optically** reconfiguring includes switching optical connections
[[which]] **that** selectively couple at least an optical transmitter and an optical
10 receiver to said first and second carrier **carriers respectively.**

[[23))] **23. (Amended) The method** ~~Method according to claim 15~~ **of Claim 14,**
wherein the step of exchanging **signals** includes feeding at each of said plurality of
nodes the corresponding subset of wavelengths to said first and, respectively, second
15 carrier. **following steps executed in the first link termination node:**

generating an optical signal carrying information;
converting the optical signal into an electrical signal;
adding information to the electrical signal;
reconverting the electrical signal into an optical signal provided with a
20 **predetermined wavelength adapted for transmission; and**
communicating the optical signal at the predetermined wavelength to a
selected one of the first and the second carriers.

[[24))] **24.** (Amended) The method ~~Method according to claim of Claim~~ 14,
wherein the step of exchanging signals includes the following steps executed in the
[[first]] second link termination node ~~of a pair~~:

- ~~generating an optical signal carrying an information;~~
- 5 — ~~converting the optical signal in a electrical signal;~~
- ~~adding to the electrical signal further information;~~
- ~~reconverting the electrical signal in an optical signal provided with a
predetermined wavelength adapted for transmission; and~~
- 10 — ~~feeding the optical signal at the predetermined wavelength to either
the first or the second carrier;~~

— ~~and the following steps executed in the second link termination node of the
same pair:~~

- receiving the optical signal at the predetermined wavelength from either a
selected one of the first [[or]] and the second ~~carrier~~ carriers;
- 15 converting the optical signal at the predetermined wavelength [[in]] into an
electrical signal;
- extracting information from the electrical signal ~~the further information~~;
- reconverting the electrical signal [[in]] into an optical signal with a
wavelength adapted for reception; and
- 20 receiving the optical signal with the wavelength adapted for reception.

25) **(Canceled)** Reconfigurable node for an autoprotected optical communication ring network, comprising a receiving/transmitting module (6) including:

- a signal input (IN_1) for the insertion into the node of a signal including information to be transmitted in the network;
- 5 - a signal output (OUT_1) for the extraction from the node of a signal including information transmitted in the network;
- a first transmitting transponder ($TxT_1(\lambda_x)$) for optically coupling to a first carrier (2) of the network and adapted to modulate a signal at a first wavelength (λ_x);
- 10 - a second transmitting transponder ($TxT_1(\lambda_y)$) for optically coupling to the first carrier (2) and adapted to modulate a signal at a second wavelength (λ_y);
- a third transmitting transponder ($TxT_2(\lambda_x)$) for optically coupling to a second carrier (3) of the network and adapted to modulate a signal at the first wavelength (λ_x);
- 15 - a first receiving transponder ($RxT_2(\lambda_x)$) for optically coupling to the second carrier (3) and adapted to demodulate a signal having the first wavelength (λ_x);
- a second receiving transponder ($RxT_2(\lambda_y)$) for optically coupling to the first carrier (2) and adapted to demodulate a signal having the second wavelength (λ_y);
- 20 - a third receiving transponder ($RxT_1(\lambda_y)$) for optically coupling to the second carrier (3) and adapted to demodulate a signal having the second wavelength (λ_y);
- 25 - reconfigurable optical connections (22-25; 31-38; 41-48; 131-136; 141-146; 231-236) to selectively connect:
 - the signal input (IN_1) either to the first transmitting transponder ($TxT_1(\lambda_x)$) to the third transmitting transponder ($TxT_2(\lambda_x)$);
 - the first receiving transponder ($RxT_2(\lambda_x)$) the third transmitting transponder ($TxT_2(\lambda_x)$);
 - 30 • the second receiving transponder ($RxT_2(\lambda_y)$) the signal output (OUT_1); and

- the third receiving transponder ($RxT_1(\lambda_y)$) either to the signal output (OUT_1) or to the second transmitting transponder ($TxT_1(\lambda_y)$)

5 26) **(Canceled)** Reconfigurable node according to claim 25, wherein the receiving/transmitting module (6) further includes:

- a further signal input (IN_2) for the insertion into the node of a signal including information to be transmitted in the network;
- a further signal output (OUT_2) for the extraction from the node of a
10 signal including information transmitted in the network;
- a fourth transmitting transponder ($TxT_2(\lambda_y)$) optically coupled to the second carrier (3) and adapted to modulate a signal at the second wavelength (λ_y); and
- a fourth receiving transponder ($RxT_1(\lambda_x)$) optically coupled to the first
15 carrier (2) and adapted to demodulate a signal having the first wavelength (λ_x);

said reconfigurable optical connections (22-25; 31-38; 41-48; 131-136; 141-146; 231-236) selectively connecting:

- the first receiving transponder ($RxT_2(\lambda_x)$) either to the third
20 transmitting transponder ($TxT_2(\lambda_x)$) or to the further signal output (OUT_2);
- the fourth receiving transponder ($RxT_1(\lambda_x)$) to the further signal output (OUT_2); and
- the further signal input (IN_2) either to the second transmitting
25 transponder ($TxT_1(\lambda_y)$) to the fourth transmitting transponder ($TxT_2(\lambda_x)$).

27) **(Canceled)** Reconfigurable node according to claim 25 or 26, characterized in that it is adapted to manage a predetermined set of wavelengths within a set of transmission wavelengths ($\lambda_1, \lambda_2, \dots, \lambda_N$) and in that it includes a first and a second optical add/drop multiplexer (4, 5) optically coupling the receiving/transmitting module (6) to said first and, respectively, second carrier (2, 3) to feed/extract said subset of wavelengths to/from said first and, respectively, second carrier (2, 3), and to pass-through the remaining wavelengths of the set of transmission wavelengths ($\lambda_1, \lambda_2, \dots, \lambda_N$).

28) **(Canceled)** Reconfigurable node according to claim 25 or 26, further including at least a first optical power splitter (221) for splitting signals coming from said at least a signal input (IN₁) and at least a second optical power splitter (222-225) for splitting signals coming from a respective one of said receiving transponders (RxTs).

15

29) **(Canceled)** Reconfigurable node according to claim 25 or 26, wherein the reconfigurable optical connections (22-25) include 2x2 switches.

30) **(Canceled)** Reconfigurable node according to claim 25 or 26, wherein the reconfigurable optical connections (31-38; 41-48; 131-136; 141-146; 231-236) include 1x2 and/or 2x1 switches.

31) **(Canceled)** Reconfigurable node according to claim 25 or 26, wherein the reconfigurable optical connections (22-25; 31-38; 41-48; 131-136; 141-146; 231-236) include discrete switching components.

32) **(Canceled)** Reconfigurable node according to claim 25 or 26, wherein the reconfigurable optical connections (22-25; 31-38; 41-48; 131-136; 141-146; 231-236) include an integrated switching matrix.

33) **(Canceled)** Reconfigurable node according to claim 25 or 26, wherein the reconfigurable optical connections (22-25; 31-38; 41-48; 131-136; 141-146; 231-236) include optical switching components selectable in the group including:

- opto-mechanical switches;
- 5 - thermo-optical switches;
- magneto-optical switches;
- liquid crystal switches;
- semiconductor switches;
- electro-optical switches;
- 10 - micro-mechanical switches; and
- lithium niobate integrated circuit switches.

34) **(Canceled)** Reconfigurable node according to claim 25 or 26, characterized in that it includes a control processing unit (16) operatively connected to said
15 receiving transponders (RxTs) and said transmitting transponders (TxTs).

35) **(Canceled)** Reconfigurable node according to claim 25 or 26, characterized in that it includes at least a further receiving/transmitting module which has substantially the same structure of said receiving/transmitting module (6) and is
20 adapted to operate with a different pair of wavelengths with respect to said receiving/transmitting module (6).

AUTOPROTECTED OPTICAL COMMUNICATION RING NETWORK

ABSTRACT OF THE DISCLOSURE

An autoprotected optical communication ring network includes a first and a second optical carrier $[(2, 3)]$ having opposite transmission directions and a plurality of optically reconfigurable nodes (20a-20f) optically connected along the first and the second optical carrier $[(2, 3)]$ and adapted to communicate in pairs by means of ~~respective~~ on links susceptible ~~[[of]]~~ to failure, the ring network having a normal operative condition in which the nodes of each pair are optically configured so as to exchange optical signals on a ~~respective~~ working arc path at a respective first wavelength (λ_x) on the first carrier $[(2)]$ and at a respective second wavelength (λ_y) different from the first wavelength (λ_x) on the second carrier $[(3)]$, the ~~respective~~ working path having a complementary arc path defining a ~~respective~~ protection arc path in which the first wavelength (λ_x) on the first carrier $[(2)]$ and the second wavelength (λ_y) on the second carrier $[(3)]$ can be used for further links ~~and the first wavelength (λ_x) on the second carrier (2) and the second wavelength (λ_y) on the first carrier (3) are reserved for protection, the ring network having also a failure operative condition in which the nodes terminating a failed link are optically reconfigured so as to exchange optical signals on the respective protection arc path at the respective second wavelength (λ_y) on the first carrier (2) and at the respective first wavelength (λ_x) on the second carrier.~~

[[Fig. 2]]